


# Xinger<sup>IV</sup>

## Ultra Low Profile 0805 20dB Directional Coupler



### Description:

The X4C40J1-20G is a low cost, low profile sub-miniature high performance 20 dB directional coupler in a new easy to use, manufacturing friendly surface mount package. It is designed for 3300 – 5000MHz applications including: LTE and 5G applications. The X4C40J1-20G is designed particularly for power and frequency detection, as well as for return loss monitoring, where tightly controlled coupling and low insertion loss is required. It can be used in high power applications up to 10 Watts.

Parts have been subjected to rigorous qualification testing and they are manufactured using materials with coefficients of thermal expansion (CTE) compatible with common substrates such as FR4, G-10, RF-35, RO4003 and polyimide. Produced with 6 of 6 RoHS compliant ENIG finish.

### Features:


- 3100-5000 MHz
- LTE, 5G Applications
- High Power
- Very Low Loss
- High Directivity
- Production Friendly
- Tape and Reel
- RoHS Compliant
- Halogen Free

### Detailed Electrical Specifications:

| Frequency   | Mean Coupling         | Insertion Loss       | Return Loss     |
|-------------|-----------------------|----------------------|-----------------|
| MHz         | dB                    | dB Max               | dB Min          |
| 3100-3300   | 20.5 ±1.5             | 0.1                  | 18              |
| 3300-4200   | 20.2 ±1.5             | 0.1                  | 18              |
| 4200-4400   | 20 ±1.5               | 0.1                  | 18              |
| 4400-5000   | 20.2 ±1.5             | 0.1                  | 18              |
| Directivity | Frequency Sensitivity | Power                | Operating Temp. |
| dB Min      | dB Max                | Avg. CW Watts @105°C | °C              |
| 17          | ±0.3                  | 10                   | -55 to +140     |
| 18          | ±0.4                  | 10                   | -55 to +140     |
| 18          | ±0.1                  | 10                   | -55 to +140     |
| 18          | ±0.3                  | 10                   | -55 to +140     |


\*\*Specification based on performance of unit properly installed on TTM Technologies Test Board with small signal applied. \*Specifications subject to change without notice. Refer to parameter definitions for details.

### Outline Drawing:



## Hybrid Coupler Pin Configuration

The X4C40J1-20G has an orientation marker to denote Pin 1. Once port one has been identified the other ports are known automatically. Please see the chart below for clarification:




**20dB Directional Coupler**

| Configuration   | Pin 1  | Pin 2    | Pin 3    | Pin 4  |
|-----------------|--------|----------|----------|--------|
| Configuration-1 | Input  | Coupled  | Isolated | Direct |
| Configuration-2 | Direct | Isolated | Coupled  | Input  |

Note: The direct port has a DC connection to the input port and the coupled port has a DC connection to the isolated port. For optimum IL and power handling performance, use Pin 1 or Pin 4 as inputs.

## Insertion Loss and Power Derating Curves



### Insertion Loss Derating:

The insertion loss, at a given frequency, of a group of couplers is measured at 25°C and then averaged. The measurements are performed under small signal conditions (i.e. using a Vector Network Analyzer). The process is repeated at -55°C, 95°C and 140°C. A best-fit line for the measured data is computed and then plotted from -55°C to 140°C.


### Power Derating:

The power handling and corresponding power derating plots are a function of the thermal resistance, mounting surface temperature (base plate temperature), maximum continuous operating temperature of the coupler, and the thermal insertion loss. The thermal insertion loss is defined in the Power Handling section of the data sheet.



As the mounting interface temperature approaches the maximum continuous operating temperature, the power handling decreases to zero.

If mounting temperature is greater than 105°C, Xinger coupler will perform reliably as long as the input power is derated to the curve above.

**Typical Performance: 3200 MHz to 5000 MHz (Configuration 1)**



**Typical Performance: 3200 MHz to 5000 MHz (Configuration 1)**





## Definition of Measured Specifications

| Parameter                                    | Definition  | Mathematical Representation  |
|--|---|--|
| <b>VSWR</b><br>(Voltage Standing Wave Ratio) | The impedance match of the coupler to a 50Ω system. A VSWR of 1:1 is optimal.   | $VSWR = \frac{V_{max}}{V_{min}}$ Vmax = voltage maxima of a standing wave<br>Vmin = voltage minima of a standing wave                      |
| <b>Return Loss</b>                           | The impedance match of the coupler to a 50Ω system. Return Loss is an alternate means to express VSWR.  | $Return\ Loss(dB) = 20\log \frac{VSWR + 1}{VSWR - 1}$  |
| <b>Mean Coupling</b>                         | At a given frequency ( $\omega_n$ ), coupling is the input power divided by the power at the coupled port. Mean coupling is the average value of the coupling values in the band. N is the number of frequencies in the band. | $Coupling(dB) = C(\omega_n) = 10\log \frac{P_{in}(\omega_n)}{P_{cpt}(\omega_n)}$ $Mean\ Coupling(dB) = \frac{\sum_{n=1}^N C(\omega_n)}{N}$ |
| <b>Insertion Loss</b>                        | The input power divided by the sum of the power at the two output ports.  | $Insertion\ Loss(dB) = 10\log \frac{P_{in}}{P_{cpt} + P_{direct}}$   |
| <b>Transmission Loss</b>                     | The input power divided by the power at the direct port.  | $10\log \frac{P_{in}}{P_{direct}}$   |
| <b>Directivity</b>                           | The power at the coupled port divided by the power at the isolated port.  | $10\log \frac{P_{cpt}}{P_{iso}}$   |
| <b>Frequency Sensitivity</b>                 | The decibel difference between the maximum in band coupling value and the mean coupling, and the decibel difference between the minimum in band coupling value and the mean coupling.   | Max Coupling (dB) – Mean Coupling (dB)<br>and<br>Min Coupling (dB) – Mean Coupling (dB)  |
| <b>Group Delay</b>                           | Group delay is average of group delay's from input port to the coupled port   | Average ( GD-C)  |
| <b>Group Delay (GD-DC)</b>                   | Group delay is average of group delay's from input port to the direct port  | Average (GD-DC)  |

## Packaging and Ordering Information

Parts are available in reels. Packaging follows EIA 481-D for reels. Parts are oriented in tape and reel as shown below. Tape and reel is available in 500 and 8000 pcs per reel.



| QUANTITY/REEL | REEL DIMENSIONS mm |        |
|---------------|--------------------|--------|
| 4000          | $\phi A$           | 177.80 |
|               | B                  | 8.00   |
|               | $\phi C$           | 50.80  |
|               | $\phi D$           | 13.00  |

**Contact us:**  
[rf&s\\_support@ttm.com](mailto:rf&s_support@ttm.com)