SIEMENS

Data sheet

3RT1065-2AT36



power contactor, AC-3e/AC-3 265 A, 132 kW / 400 V AC (50-60 Hz) / DC Uc: 575-600 V 3-pole, auxiliary contacts 2 NO + 2 NC drive: conventional main circuit: busbar control and auxiliary circuit: spring-loaded terminal

product brand name	SIRIUS
product designation	Power contactor
product type designation	3RT1
General technical data	
size of contactor	S10
product extension	
 function module for communication 	No
auxiliary switch	Yes
power loss [W] for rated value of the current	
 at AC in hot operating state 	54 W
 at AC in hot operating state per pole 	18 W
 without load current share typical 	7.4 W
insulation voltage	
 of main circuit with degree of pollution 3 rated value 	1 000 V
 of auxiliary circuit with degree of pollution 3 rated value 	500 V
surge voltage resistance	
 of main circuit rated value 	8 kV
 of auxiliary circuit rated value 	6 kV
maximum permissible voltage for protective separation between coil and main contacts according to EN 60947-1	690 V
shock resistance at rectangular impulse	
• at AC	8,5g / 5 ms, 4,2g / 10 ms
• at DC	8,5g / 5 ms, 4,2g / 10 ms
shock resistance with sine pulse	
• at AC	13,4g / 5 ms, 6,5g / 10 ms
• at DC	13,4g / 5 ms, 6,5g / 10 ms
mechanical service life (operating cycles)	
 of contactor typical 	10 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	05/01/2012
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
 during operation 	-25 +60 °C
 during storage 	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %

Main circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
operating voltage	
• at AC-3 rated value maximum	1 000 V
 at AC-3e rated value maximum 	1 000 V
operational current	
 at AC-1 at 400 V at ambient temperature 40 °C rated value 	330 A
• at AC-1	
— up to 690 V at ambient temperature 40 °C rated value	330 A
— up to 690 V at ambient temperature 60 °C rated value	300 A
— up to 1000 V at ambient temperature 40 °C rated value	150 A
— up to 1000 V at ambient temperature 60 °C rated value	150 A
• at AC-3	
— at 400 V rated value	265 A
— at 500 V rated value	265 A
— at 690 V rated value	265 A
— at 1000 V rated value	95 A
• at AC-3e	
— at 400 V rated value	265 A
— at 500 V rated value	265 A
— at 690 V rated value	265 A
— at 1000 V rated value	95 A
• at AC-4 at 400 V rated value	230 A
 at AC-5a up to 690 V rated value 	290 A
 at AC-5b up to 400 V rated value 	219 A
● at AC-6a	
— up to 230 V for current peak value n=20 rated value	265 A
— up to 400 V for current peak value n=20 rated value	265 A
— up to 500 V for current peak value n=20 rated value	265 A
— up to 690 V for current peak value n=20 rated value	265 A
— up to 1000 V for current peak value n=20 rated value	95 A
• at AC-6a	
 — up to 230 V for current peak value n=30 rated value 	184 A
 — up to 400 V for current peak value n=30 rated value 	184 A
 — up to 500 V for current peak value n=30 rated value 	184 A
 — up to 690 V for current peak value n=30 rated value 	184 A
 — up to 1000 V for current peak value n=30 rated value 	95 A
minimum cross-section in main circuit at maximum AC-1 rated value	185 mm²
operational current for approx. 200000 operating cycles at AC-4	
• at 400 V rated value	117 A
• at 690 V rated value	105 A
operational current	
 at 1 current path at DC-1 	
— at 24 V rated value	300 A
— at 60 V rated value	300 A
— at 110 V rated value	33 A
— at 220 V rated value	3.8 A
— at 440 V rated value	0.9 A
— at 600 V rated value	0.6 A
 with 2 current paths in series at DC-1 	
— at 24 V rated value	300 A
— at 60 V rated value	300 A
— at 110 V rated value	300 A

— at 220 V rated value	300 A
— at 440 V rated value	4 A
— at 600 V rated value	2 A
 with 3 current paths in series at DC-1 	
— at 24 V rated value	300 A
— at 60 V rated value	300 A
— at 110 V rated value	300 A
— at 220 V rated value	300 A
— at 440 V rated value	11 A
— at 600 V rated value	5.2 A
 at 1 current path at DC-3 at DC-5 	
— at 24 V rated value	300 A
— at 60 V rated value	11 A
— at 110 V rated value	3 A
— at 220 V rated value	0.6 A
— at 440 V rated value	0.18 A
— at 600 V rated value	0.125 A
 with 2 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	300 A
— at 60 V rated value	300 A
— at 110 V rated value	300 A
— at 220 V rated value	2.5 A
— at 440 V rated value	0.65 A
— at 600 V rated value	0.37 A
 with 3 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	300 A
— at 60 V rated value	300 A
— at 110 V rated value	300 A
— at 220 V rated value	300 A
— at 440 V rated value	1.4 A
— at 600 V rated value	0.75 A
operating power	
• at AC-3	
— at 230 V rated value	75 kW
— at 400 V rated value	132 kW
— at 500 V rated value	160 kW
— at 690 V rated value	250 kW
— at 1000 V rated value	132 kW
• at AC-3e	
— at 230 V rated value	75 kW
— at 400 V rated value	132 kW
— at 500 V rated value	160 kW
— at 690 V rated value	250 kW
— at 1000 V rated value	132 kW
operating power for approx. 200000 operating cycles at AC-	
4	
• at 400 V rated value	66 kW
• at 690 V rated value	102 kW
operating apparent power at AC-6a	
 up to 230 V for current peak value n=20 rated value 	100 000 kVA
 up to 400 V for current peak value n=20 rated value 	180 000 VA
 up to 500 V for current peak value n=20 rated value 	220 000 VA
 up to 690 V for current peak value n=20 rated value 	310 000 VA
 up to 1000 V for current peak value n=20 rated value 	160 000 VA
operating apparent power at AC-6a	
 up to 230 V for current peak value n=30 rated value 	70 000 VA
 up to 400 V for current peak value n=30 rated value 	120 000 VA
 up to 500 V for current peak value n=30 rated value 	150 000 VA
 up to 690 V for current peak value n=30 rated value 	220 000 VA
 up to 1000 V for current peak value n=30 rated value 	160 000 VA
short-time withstand current in cold operating state up to	

40 °C	
 limited to 1 s switching at zero current maximum 	4 880 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 5 s switching at zero current maximum 	4 045 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 10 s switching at zero current maximum 	2 785 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 30 s switching at zero current maximum 	1 664 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 60 s switching at zero current maximum 	1 276 A; Use minimum cross-section acc. to AC-1 rated value
no-load switching frequency	
• at AC	2 000 1/h
• at DC	2 000 1/h
operating frequency	
• at AC-1 maximum	800 1/h
at AC-2 maximum	250 1/h
• at AC-3 maximum	500 1/h
at AC-3e maximum	500 1/h
• at AC-4 maximum	130 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	AC/DC
control supply voltage at AC	
• at 50 Hz rated value	575 600 V
• at 60 Hz rated value	575 600 V
control supply voltage at DC	
rated value	575 600 V
operating range factor control supply voltage rated value of	575 000 V
magnet coil at DC	
initial value	0.8
• full-scale value	1.1
operating range factor control supply voltage rated value of	
magnet coil at AC	
● at 50 Hz	0.8 1.1
• at 60 Hz	0.8 1.1
design of the surge suppressor	with varistor
apparent pick-up power of magnet coil at AC	
● at 50 Hz	590 VA
• at 60 Hz	590 VA
inductive power factor with closing power of the coil	
• at 50 Hz	0.9
• at 60 Hz	0.9
apparent holding power of magnet coil at AC	
• at 50 Hz	6.7 VA
• at 60 Hz	6.7 VA
inductive power factor with the holding power of the coil	
• at 50 Hz	0.9
• at 60 Hz	0.9
closing power of magnet coil at DC	650 W
holding power of magnet coil at DC	7.4 W
closing delay	00 05
• at AC	30 95 ms
• at DC	30 95 ms
opening delay	10 00
• at AC	40 80 ms
• at DC	40 80 ms
arcing time	10 15 ms
control version of the switch operating mechanism	Standard A1 - A2
Auxiliary circuit	0
number of NC contacts for auxiliary contacts instantaneous contact	2
number of NO contacts for auxiliary contacts instantaneous contact	2
operational current at AC-12 maximum	10 A
operational current at AC-15	
• at 230 V rated value	6 A
• at 400 V rated value	3 A

• at 500 V rated value	2 A
• at 690 V rated value	1 A
operational current at DC-12	
• at 24 V rated value	10 A
 at 48 V rated value 	6 A
 at 60 V rated value 	6 A
• at 110 V rated value	3 A
• at 125 V rated value	2 A
at 220 V rated value	1 A
• at 600 V rated value	0.15 A
operational current at DC-13	
• at 24 V rated value	10 A
• at 48 V rated value	2 A
• at 60 V rated value	2 A
• at 110 V rated value	1 A
• at 125 V rated value	0.9 A
• at 220 V rated value	0.3 A
 at 600 V rated value 	0.1 A
contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
at 480 V rated value	240 A
at 600 V rated value	240 A
yielded mechanical performance [hp]	
• for 3-phase AC motor	
— at 200/208 V rated value	75 hp
— at 220/230 V rated value	100 hp
— at 460/480 V rated value	200 hp
- at 575/600 V rated value	250 hp
contact rating of auxiliary contacts according to UL	A600 / Q600
	A0007 @000
Short-circuit protection	
Short-circuit protection	
design of the fuse link	
design of the fuse link • for short-circuit protection of the main circuit	
 design of the fuse link for short-circuit protection of the main circuit — with type of coordination 1 required 	gG: 500 A (690 V, 100 kA)
design of the fuse link • for short-circuit protection of the main circuit	gG: 500 A (690 V, 100 kA) gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA)
 design of the fuse link for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required 	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA)
 design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required 	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50
 design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions 	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) kA) gG: 10 A (500 V, 1 kA)
 design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required 	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA)
 design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions 	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface
design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position 	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — downwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm 10 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — a the side	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm 10 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — downwards — at the side • for grounded parts	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 20 mm 10 mm 0 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — at the side • for grounded parts — forwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 20 mm 10 mm 0 mm 20 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — at the side • for grounded parts — upwards — upwards — upwards — upwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm 0 mm 20 mm 10 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/mounting/dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — downwards — at the side • for grounded parts — downwards — at the side — downwards — upwards — downwards — at the side — downwards — at the side — downwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm 0 mm 20 mm 10 mm 10 mm
design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — at the side • for grounded parts — forwards — upwards — odwnwards — odwnwards — forwards — upwards — forwards — forwards — forwards — forwards — forwards — ownwards — for live parts	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm 0 mm 20 mm 10 mm 10 mm 10 mm
design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - at the side - at the side - downwards - at the side - forwards - at the side - forwards - at the side - forwards - at the side - for live parts - forwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm
design of the fuse link • for short-circuit protection of the main circuit - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - forwards - upwards - forwards - upwards - at the side - forwards - upwards - upwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) (A) (G: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 20 mm 10 mm 0 mm 10 mm 1
design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - at the side - at the side - downwards - at the side - forwards - at the side - forwards - at the side - forwards - at the side - for live parts - forwards	gG: 400 A (690 V, 100 kA), aM: 315 A (690 V, 50 kA), BS88: 400 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 210 mm 145 mm 202 mm 10 mm 0 mm 20 mm 10 mm 10 mm 10 mm 10 mm 20 mm

hung of clostril-	ls					
type of electrical cor			Connection her			
for main curren			Connection bar			
 for auxiliary and at contactor for 			spring-loaded terminals Spring-type terminals			
	at contactor for auxiliary contacts					
of magnet coil width of connection	bar		Spring-type terminals			
thickness of connection			25 mm 6 mm			
diameter of holes	tion bar		11 mm			
number of holes			1			
	tor cross-section for main		I			
 stranded 	tor cross-section for main	rcontacts	70 240 mm²			
	tor cross-section for auxi	liary contacts	70 240 mm			
 solid or strande 		nary contacts	0.25 2.5 mm²			
			0.25 2.5 mm ²			
-	with core end processing without core end processin	a	0.25 2.5 mm ²			
· · · · · · · · · · · · · · · · · · ·		-	0.20 2.0 11111-			
	conductor cross-sections	•				
 for auxiliary cor 	และเร		$2x (0.25 - 2.5 mm^2)$			
— solid	randad		2x (0.25 2.5 mm ²)			
— solid or st		ing	$2x (0,25 \dots 2,5 \text{ mm}^2)$			
	nded with core end process	-	2x (0.25 1.5 mm ²)			
5	nded without core end proc	essing	2x (0.25 2.5 mm ²)			
AWG number as cod	s for auxiliary contacts led connectable conducto	or cross	2x (24 14)			
section	4		04 44			
 for auxiliary cor 			24 14			
afety related data						
product function			N .			
	iccording to IEC 60947-4-1		Yes			
 positively driven operation according to IEC 60947-5-1 			No			
B10 value with high demand rate according to SN 31920		1 000 000				
T1 value for proof test 61508	interval or service life acco	ording to IEC	20 a			
protection class IP on the front according to IEC 60529		IP00; IP20 with box terminal/cover				
-	the front according to IEC	60529	finger-safe, for vertical cont	tact from the front with box ter	rminal/cover	
suitability for use						
 safety-related s 	-		Yes			
ertificates/ approvals	;					
General Product Ap	proval					
(A)	Confirmation		Ē	KC	rnr	
QĽ		<u></u>	(NL)		EHC	
CSA		ccc	UL		6116	
	_					
EMC	Functional Safety/Safety of Ma-	Declaration of	Conformity	Test Certificates		
	chinery	Declaration of		rost certificates		
-	-			0.000		
A	Type Examination Cer- tificate	UK	"	Special Test Certific- ate	<u>Type Test Certific</u> ates/Test Report	
## L Z . N	monto	20	עכ			
<u>v</u>		LH	EG-Konf.			
RCM						
RCM						
RCM					othor	
RCM					other	
RCM		Æ	æ		other Miscellaneous	
RCM	Lloyds	6		\bigcirc		
	Llovds Register	6		DNV-GL		
Marine / Shipping	Llovds Register us	PRS	RMRS RMRS	DNV-GL		

7/10/2023

other			Railway		Environment
<u>Confirmation</u>	<u>Miscellaneous</u>	<u>Confirmation</u>	<u>Special Test Certific-</u> <u>ate</u>	Vibration and Shock	Environmental Con- firmations

Siemens has decided to exit the Russian market (see here).
https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business
Sigmons is working on the renewal of the current EAC cortificates

Siemens is working on the renewal of the current EAC certificates. Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

Further information

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT1065-2AT36

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT1065-2AT36

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT1065-2AT36


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)


http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT1065-2AT36&lang=en


Characteristic: Tripping characteristics, I²t, Let-through current


https://support.industry.siemens.com/cs/ww/en/ps/3RT1065-2AT36/char

Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT1065-2AT36&objecttype=14&gridview=view1









last modified:

5/8/2023 🖸