SIEMENS

Data sheet 3RU2126-1CC0



Overload relay 1.8...2.5 A Thermal For motor protection Size S0, Class 10 Contactor mounting Main circuit: Spring-type terminal Auxiliary circuit: spring-type terminal Manual-Automatic-Reset

product type designation product type designation 3RU2 General technical data size of overload relay size of contactor can be combined company-specific power loss [W] for rated value of the current at AC in hot operating state • per pole insulation voltage with degree of pollution 3 at AC rated value surge voltage resistance rated value maximum permissible voltage for protective separation in networks with grounded star point • between auxiliary and auxiliary circuit • between main and auxiliary circuit	
size of overload relay size of contactor can be combined company-specific power loss [W] for rated value of the current at AC in hot operating state	
size of overload relay size of contactor can be combined company-specific power loss [W] for rated value of the current at AC in hot operating state • per pole insulation voltage with degree of pollution 3 at AC rated value surge voltage resistance rated value maximum permissible voltage for protective separation in networks with grounded star point • between auxiliary and auxiliary circuit • between auxiliary and auxiliary circuit • between main and auxiliary circuit	
size of contactor can be combined company-specific power loss [W] for rated value of the current at AC in hot operating state • per pole insulation voltage with degree of pollution 3 at AC rated value surge voltage resistance rated value maximum permissible voltage for protective separation in networks with grounded star point • between auxiliary and auxiliary circuit • between auxiliary and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit 440 V • between main and auxiliary circuit 440 V	
power loss [W] for rated value of the current at AC in hot operating state	
operating state • per pole insulation voltage with degree of pollution 3 at AC rated value surge voltage resistance rated value maximum permissible voltage for protective separation in networks with grounded star point • between auxiliary and auxiliary circuit • between auxiliary and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit 440 V • between main and auxiliary circuit 440 V	
insulation voltage with degree of pollution 3 at AC rated value surge voltage resistance rated value maximum permissible voltage for protective separation in networks with grounded star point • between auxiliary and auxiliary circuit • between auxiliary and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit 440 V • between main and auxiliary circuit 440 V	
surge voltage resistance rated value maximum permissible voltage for protective separation in networks with grounded star point • between auxiliary and auxiliary circuit • between auxiliary and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit 440 V	
maximum permissible voltage for protective separation in networks with grounded star point • between auxiliary and auxiliary circuit • between auxiliary and auxiliary circuit • between main and auxiliary circuit	
networks with grounded star point • between auxiliary and auxiliary circuit • between auxiliary and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit • between main and auxiliary circuit 440 V • between main and auxiliary circuit 440 V	
 between auxiliary and auxiliary circuit between main and auxiliary circuit between main and auxiliary circuit 440 V between main and auxiliary circuit 440 V 	
 between main and auxiliary circuit between main and auxiliary circuit 440 V 440 V 	
between main and auxiliary circuit 440 V	
· · · · · · · · · · · · · · · · · · ·	
shock resistance according to IEC 60068-2-27 8g / 11 ms	
type of protection according to ATEX directive 2014/34/EU Ex II (2) GD	
certificate of suitability according to ATEX directive 2014/34/EU DMT 98 ATEX G 001	
reference code according to IEC 81346-2 F	
Substance Prohibitance (Date) 10/01/2009	
Ambient conditions	
installation altitude at height above sea level maximum 2 000 m	
ambient temperature	
• during operation -40 +70 °C	
• during storage -55 +80 °C	
• during transport -55 +80 °C	
temperature compensation -40 +60 °C	
relative humidity during operation 10 95 %	
Main circuit	
number of poles for main current circuit 3	
adjustable current response value current of the current- dependent overload release	
operating voltage	
• rated value 690 V	
• at AC-3e rated value maximum 690 V	
operating frequency rated value 50 60 Hz	
operational current rated value 2.5 A	
operational current at AC-3e at 400 V rated value 2.5 A	
operating power	

• at AC-3	
● at AC-3 — at 400 V rated value	0.75 kW
— at 500 V rated value	1.1 kW
— at 690 V rated value	1.5 kW
at AC-3e • at AC-3e	1.5 KVV
	0.75 NN
— at 400 V rated value	0.75 kW 1.1 kW
— at 500 V rated value — at 690 V rated value	1.5 kW
Auxiliary circuit	1.5 KW
design of the auxiliary switch	integrated
number of NC contacts for auxiliary contacts	1
• note	for contactor disconnection
number of NO contacts for auxiliary contacts	1
• note	for message "Tripped"
number of CO contacts for auxiliary contacts	0
operational current of auxiliary contacts at AC-15	
• at 24 V	3 A
• at 110 V	3 A
• at 120 V	3 A
• at 125 V	3 A
• at 230 V	2 A
• at 400 V	1 A
• at 690 V	0.75 A
operational current of auxiliary contacts at DC-13	
• at 24 V	2 A
• at 60 V	0.3 A
• at 110 V	0.22 A
• at 125 V	0.22 A
• at 220 V	0.11 A
contact rating of auxiliary contacts according to UL	B600 / R300
Protective and monitoring functions	
trip class	CLASS 10
design of the overload release	thermal
UII /CSA ratings	
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	0.5.4
full-load current (FLA) for 3-phase AC motor • at 480 V rated value	2.5 A
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value	2.5 A 2.5 A
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection	
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link	2.5 A
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required	
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	2.5 A fuse gG: 6 A, quick: 10 A
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position	2.5 A fuse gG: 6 A, quick: 10 A any
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No spring-loaded terminals spring-loaded terminals
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No spring-loaded terminals spring-loaded terminals
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections	2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No spring-loaded terminals spring-loaded terminals
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts	fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No spring-loaded terminals spring-loaded terminals Top and bottom
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded	fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No spring-loaded terminals spring-loaded terminals Top and bottom
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded — finely stranded with core end processing	fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No spring-loaded terminals spring-loaded terminals Top and bottom 1x (1 10 mm²) 1x (1 6 mm²)
full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded — finely stranded with core end processing — finely stranded without core end processing	fuse gG: 6 A, quick: 10 A any Contactor mounting 102 mm 45 mm 84 mm No spring-loaded terminals spring-loaded terminals Top and bottom 1x (1 10 mm²) 1x (1 6 mm²) 1x (1 6 mm²)

• for auxiliary contacts - solid or stranded 2x (0.5 ... 2.5 mm²) - finely stranded with core end processing 2x (0.5 ... 1.5 mm²), 2x (0.75 ... 2.5 mm²) - finely stranded without core end processing 2x (0.5 ... 1.5 mm²) • for AWG cables for auxiliary contacts 2x (20 ... 14) design of screwdriver shaft Diameter 3 mm size of the screwdriver tip 3,0 x 0,5 mm Safety related data failure rate [FIT] with low demand rate according to SN 31920 50 FIT MTTF with high demand rate 2 280 a T1 value for proof test interval or service life according to IEC 20 a 61508 IP20 protection class IP on the front according to IEC 60529 touch protection on the front according to IEC 60529 finger-safe, for vertical contact from the front display version for switching status Slide switch

Certificates/ approvals

General Product Approval

For use in hazardous locations



Confirmation









Declaration of Conformity

Test Certificates

Marine / Shipping





Type Test Certificates/Test Report

Special Test Certificate





Marine / Shipping

other











Confirmation

Railway

Vibration and Shock

Further information

Siemens has decided to exit the Russian market (see here).

 $\underline{\text{https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business}}$

Siemens is working on the renewal of the current EAC certificates.

Please contact your ocal Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RU2126-1CC0

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RU2126-1CC0

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)


https://support.industry.siemens.com/cs/ww/en/ps/3RU2126-1CC0


 $Image\ database\ (product\ images,\ 2D\ dimension\ drawings,\ 3D\ models,\ device\ circuit\ diagrams,\ EPLAN\ macros,\ ...)$


http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RU2126-1CC0&lang=en


 $\label{eq:Characteristic:Tripping characteristics, I^2t, Let-through current} \end{substitute}$

https://support.industry.siemens.com/cs/ww/en/ps/3RU2126-1CC0/cha









last modified: 3/8/2022 🖸