EMI Filters AKCL 100 Small Signal Feed-Through Filters



Overview

A feed-through filter series utilizing discoidal ceramics for the capacitive element. This robust multilayer structure provides solutions for EMI problems from 30kHz to 1GHz. The filters are housed in robust, sealed metal cylinders with threaded construction, and offer a range of terminal options.

- Very high attenuation level throughout frequency spectrum
- Capacitor value 1.2 µF rated 80 VDC
- · Wide choice of performance options
- Excellent temperature stability
- Hermetic construction

Applications

Specifically designed for military, industrial, telecom and medical applications.



Technical Specifications

| ltem | Parameters/ Characteristics | | |
|-------------------|--------------------------------|--|--|
| Rated Voltage | 50 VAC 80 VDC | | |
| Rated Current | 0.06 – 15 A | | |
| Capacitance | 1.2 µF | | |
| Rated Temperature | 40°C | | |
| Temperature range | -55°C to 125°C | | |
| Climate Category | 55/125/56 | | |
| Voltage Test | 200 VDC | | |

Typical Electrical Schematic





Technical Specifications cont.

| Part Number | Rated Current at 40°C (A) | RDC (mΩ) | ССТ | |
|---------------------|---------------------------|----------|-----|--|
| AKCL100412RK(1)1(2) | 15 | 0.08 | 1 | |
| AKCL100412RK(1)3(2) | 15 | 0.08 | 1 | |
| AKCL100412RA(1)5(2) | 0412RA(1)5(2) 0.06 70 | | 1 | |
| AKCL101412RA(1)5(2) | 0.06 70 | | 2 | |
| AKCL100412RB(1)5(2) | 412RB(1)5(2) 0.15 12 | | 1 | |
| AKCL101412RB(1)5(2) | 0.15 | 12 | 2 | |
| AKCL100412RC(1)5(2) | 0.25 | 4 | 1 | |
| AKCL101412RC(1)5(2) | 0.25 | 5 | 2 | |
| AKCL100412RD(1)5(2) | 0.3 | 2.3 | 1 | |
| AKCL101412RD(1)5(2) | 0.3 | 2.3 | 2 | |
| AKCL100412RE(1)5(2) | 0.45 | 1.2 | 1 | |
| AKCL101412RE(1)5(2) | 0.45 | 1.2 | 2 | |
| AKCL100412RJ(1)5(2) | 10 | 0.01 | 1 | |
| AKCL101412RJ(1)5(2) | 10 | 0.01 | 2 | |

(1) Termination: W = Wire

T = Tag

(2) Case fnish:

```
T = Tin plated
S = Silver plated
```

G = Gold plated



Environmental Compliance

KEMET EMI filters are RoHS Compliant.




Typical Insertion Loss

| Part Number | 30 kHz (dB) | 150 kHz (dB) | 300 kHz (dB) | 1 MHz (dB) | 10 MHz (dB) | 1 GHz (dB) |
|-----------------|----------------|-----------------|-----------------|---------------|----------------|---------------|
| AKCL100412RK-1- | 15 | 28 | 34 | 44 | 60 | 70 |
| AKCL100412RK-3- | 15 | 28 | 34 | 44 | 60 | 70 |
| AKCL100412RA-5- | 44 | 70 | 70 | 70 | 70 | 70 |
| AKCL101412RA-5- | 44 | 70 | 70 | 70 | 70 | 70 |
| AKCL100412RB-5- | 24 | 52 | 64 | 70 | 70 | 70 |
| AKCL101412RB-5- | 24 | 52 | 64 | 70 | 70 | 70 |
| AKCL100412RC-5- | 18 | 42 | 56 | 70 | 70 | 70 |
| AKCL101412RC-5- | 18 | 42 | 56 | 70 | 70 | 70 |
| AKCL100412RD-5- | 16 | 35 | 44 | 62 | 70 | 70 |
| AKCL101412RD-5- | 16 | 35 | 44 | 62 | 70 | 70 |
| AKCL100412RE-5- | 15 | 31 | 37 | 55 | 70 | 70 |
| AKCL101412RE-5- | 15 | 31 | 37 | 55 | 70 | 70 |
| AKCL100412RJ-5- | 15 | 28 | 33 | 44 | 70 | 70 |
| AKCL101412RJ-5- | 15 | 28 | 33 | 44 | 70 | 70 |



Mechanical Dimensions – Millimeters



| Part Number | Dimensions (mm) | | | | | | | |
|-----------------|-----------------|---------------|----------------------|-----------------------|----------------------|-----------------------|----------|--------------|
| | L1 Maximum | L2 Maximum | L3 Maximum Tag | L3 Maximum Wire | L4 Maximum Tag | L4 Maximum Wire | Wire Ø D | Thread |
| AKCL100412RK-1- | 4.6 | 4.85 | 8.25 | 17 | 8.9 | 17.2 | 1 | 1/4 - 28 UNF |
| AKCL100412RK-3- | 4.6 | 4.85 | 8.5 | 17 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL100412RA-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL101412RA-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL100412RB-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL101412RB-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL100412RC-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL101412RC-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL100412RD-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL101412RD-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL100412RE-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL101412RE-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL100412RJ-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |
| AKCL101412RJ-5- | 14.7 | 4.85 | 18.8 | 27 | 8.9 | 17.2 | 1.5 | 1/4 - 28 UNF |



KEMET Electronics Corporation Sales Offices

For a complete list of our global sales offices, please visit www.kemet.com/sales.

Disclaimer

YAGEO Corporation and its affiliates do not recommend the use of commercial or automotive grade products for high reliability applications or manned space flight.

All product specifications, statements, information and data (collectively, the "Information") in this datasheet are subject to change. The customer is responsible for checking and verifying the extent to which the Information contained in this publication is applicable to an order at the time the order is placed. All Information given herein is believed to be accurate and reliable, but it is presented without guarantee, warranty, or responsibility of any kind, expressed or implied.

Statements of suitability for certain applications are based on KEMET Electronics Corporation's ("KEMET") knowledge of typical operating conditions for such applications, but are not intended to constitute – and KEMET specifically disclaims – any warranty concerning suitability for a specific customer application or use. The Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by KEMET with reference to the use of KEMET's products is given gratis, and KEMET assumes no obligation or liability for the advice given or results obtained.

Although KEMET designs and manufactures its products to the most stringent quality and safety standards, given the current state of the art, isolated component failures may still occur. Accordingly, customer applications which require a high degree of reliability or safety should employ suitable designs or other safeguards (such as installation of protective circuitry or redundancies) in order to ensure that the failure of an electrical component does not result in a risk of personal injury or property damage.

Although all product-related warnings, cautions and notes must be observed, the customer should not assume that all safety measures are indicated or that other measures may not be required.

KEMET is a registered trademark of KEMET Electronics Corporation.