

Strain- and Bridge-Based Measurements

NI USB-9237

- Full-, half-, and quarter-bridge (120/350 Ω) completion¹
- Bus powered
- Built-in excitation up to 10 V
- Up to 50 kS/s/ch sample rate
- Simultaneous acquisition with four ADCs
- Quick sensor connect with RJ50 connectors
- TEDS (IEEE 1454.1) compatible
- External excitation input through analog bridge (optional)

¹Quarter bridge requires accessory.

Operating Systems

- Windows Vista/XP/2000

Compatible Software

- LabVIEW
- LabWindows™/CVI
- Measurement Studio
- Visual Basic 6.0
- C# and Visual Basic .NET
- ANSI C/C++

Measurement Services Software (included)

- NI-DAQmx driver software
- Measurement & Automation Explorer configuration utility
- LabVIEW SignalExpress LE data-logging software



Overview

The National Instruments USB-9237 combines performance and portability by making the NI 9237 C Series module compatible with the bus-powered USB carrier for C Series modules. This module is ideal for laptop applications because the USB port on the laptop powers all acquisition and sensor excitation.

High-Speed Measurements

The NI USB-9237 module can take measurements at up to 50 kS/s on four channels simultaneously and continuously stream the data back over a Hi-Speed USB interface to serve applications from static load or fatigue testing to high-speed fracture tests.

Sensor Compatibility

With full-, half-, and quarter-bridge completion, the USB-9237 can measure a variety of load, force, and torque cells as well as some pressure transducers and most strain gages.¹

Safety Isolation

- 30 V of overvoltage protection
- 60 V of CAT I channel-to-earth ground isolation
- 1000 V of transient withstand isolation

¹Quarter bridge requires accessory.

Connectivity

The USB-9237 uses four standard RJ50 connectors for rapid sensor connection. You can add an RJ50 connector to any sensor using a crimping tool, making sensor removal and insertion as easy as connecting a PC to a network. For screw-terminal connectivity, the NI 9949 accessory kit converts from RJ50 to 10 screw terminals. RJ50 cable kits are available in quantities of four 2 m cables and one 10 m cable. For custom sensor wiring, cable kits are available with an RJ50 connector on one end and 10 signal wires on the other.

Software

The USB-9237 is shipped with the standard NI-DAQmx bundle that includes Measurement & Automation Explorer (MAX) for configuration and testing; LabVIEW SignalExpress LE for out-of-the-box measurements, logging, and data display; and an API/driver for languages such as LabVIEW, ANSI C, C#, Visual Basic .NET, Visual Basic 6.0, Measurement Studio, and LabWindows/CVI.

Strain- and Bridge-Based Measurements

Specifications

>> For complete specifications, see the *NI USB-9237 User Guide and Specifications* manual at ni.com/manuals.

Input Characteristics

Number of channels.....	4
Bridge completion	
Full and half	Internal
Quarter	External
ADC resolution.....	24 bits
Type of ADC	Delta-sigma (with analog prefiltering)
Sampling mode	Simultaneous
Data rates (f_s)	(50 kS/s)/n, n= 1, 1, ...31
Master timebase (internal)	
Frequency.....	12.8 MHz
Accuracy	±100 ppm max
Nominal full-scale range	±25 mV/V
Scaling coefficient	2.9802 nV/V per LSB
Overvoltage protection	
between any two terminals	±30 V
Accuracy	

Error ¹	Percent of Reading	Percent of Range ²
Calibrated max (-40 to 70 °C)	0.20%	0.25%
Calibrated typ (25 °C, ±5 °C)	0.05%	0.05%
Uncalibrated max (-40 to 70 °C)	0.60%	0.35%
Uncalibrated typ (25 °C, ±5 °C)	0.20%	0.1%

¹ Excluding offset null or shunt calibration. ² Range equals 25 mV/V.

Gain drift	10 ppm/°C max
Offset drift	
2.5 V excitation	0.6 μV/V per °C
3.3 V excitation	0.5 μV/V per °C
5 V excitation	0.3 μV/V per °C
10 V excitation	0.2 μV/V per °C

Safety

Safety Voltages

Connect only voltages that are within these limits.
Between any two terminals ±30 V max

Isolation

Channel-to-channel	No isolation between channels
Channel-to-earth ground	
Continuous	60 VDC, Measurement Category I
Withstand	1,000 V _{rms} , verified by a 5 s dielectric withstand test

Excitation Voltages

Although the sensor industry does not recognize a single standard excitation voltage level, excitation voltage levels of between 2.5 and 10 V are common. You can program the USB-9237 to supply 2.5, 3.3, 5, or 10 V of excitation voltage, and the module can provide up to 150 mW of excitation power. Unless you supply external excitation voltage, National Instruments recommends that you set the excitation voltage to a value that keeps the total power below 150 mW. The USB-9237 automatically reduces internal excitation voltages as needed to stay below 150 mW.

The power consumed by a single bridge is

$$\frac{V_{ex}^2}{R}$$

where R is the total resistance of the bridge.

For a full bridge, R is equal to the resistance of each element. For a half or quarter bridge, R is equal to two times the resistance of each element.

With the 150 mW limit, you can power full and half bridges as follows:


- Four 350 Ω half bridges at 5.0 V
- Four 350 Ω full bridges at 3.3 V
- Four 120 Ω half bridges at 2.5 V

If you need an excitation voltage greater than 150 mW, use the four-position external excitation voltage connector to connect an external excitation source to the USB-9237.

Channel Signal Names

RJ50 (10p10c) Modular Plug and Receptacle Pin Numbers	RJ50 Pin	RJ45 Pin	Signal Name	Signal Description
	1	–	SC	Shunt calibration
	2	1	AI+	Positive input signal
	3	2	AI-	Negative input signal
	4	3	RS+	Positive remote sense signal
	5	4	RS-	Negative remote sense signal
	6	5	EX+	Positive excitation signal ¹
	7	6	EX-	Negative excitation signal ¹
	8	7	T+	TEDS DATA
	9	8	T-	TEDS Return ¹
	10	–	SC	Shunt calibration

¹ These signals are shared by all four RJ50 connectors on the USB-9237.



Strain- and Bridge-Based Measurements

Accessories

There are several options for connecting signals to the USB-9237, as shown in figures 1 and 2.



Figure 1. NI 9237 with RJ50 to 10 m Signal Wire Cable



Figure 2. NI 9237 with RJ50 Cable and Screw-Terminal Accessories

Ordering Information

NI USB-9237 (carrier, module, and USB cable)	780137-01
NI 9945 (1/4 bridge, 350 Ω , qty 4)	194739-01
NI 9944 (1/4 bridge, 120 Ω , qty 4)	194738-01
NI 9949 (RJ50 to screw terminal)	196809-01
NI 9942 (excitation connector)	194611-01
RJ50 cable, 2 m (qty 4)	194612-02
RJ50 cable, 10 m (qty 1)	194612-10
RJ50 to signal wire cable, 2 m (qty 4)	195950-02
RJ50 to signal wire cable, 10 m (qty 1)	195950-10

BUY NOW!

For complete product specifications, pricing, and accessory information, call 800 813 3693 (U.S.) or go to ni.com/compactdaq.

NI Services and Support



NI has the services and support to meet your needs around the globe and through the application life cycle – from planning and development through deployment and ongoing maintenance. We offer services and service levels to meet customer requirements in research, design, validation, and manufacturing. Visit ni.com/services.

Training and Certification

NI training is the fastest, most certain route to productivity with our products. NI training can shorten your learning curve, save development time, and reduce maintenance costs over the application life cycle. We schedule instructor-led courses in cities worldwide, or we can hold a course at your facility. We also offer a professional certification program that identifies individuals who have high levels of skill and knowledge on using NI products. Visit ni.com/training.

Professional Services

Our NI Professional Services team is composed of NI applications and systems engineers and a worldwide National Instruments Alliance Partner program of more than 600 independent consultants and

integrators. Services range from start-up assistance to turnkey system integration. Visit ni.com/alliance.



OEM Support

We offer design-in consulting and product integration assistance if you want to use our products for OEM applications. For information about special pricing and services for OEM customers, visit ni.com/oem.

Local Sales and Technical Support

In offices worldwide, our staff is local to the country, giving you access to engineers who speak your language. NI delivers industry-leading technical support through online knowledge bases, our applications engineers, and access to 14,000 measurement and automation professionals within NI Developer Exchange forums. Find immediate answers to your questions at ni.com/support.

We also offer service programs that provide automatic upgrades to your application development environment and higher levels of technical support. Visit ni.com/ssp.

Hardware Services

NI Factory Installation Services

NI Factory Installation Services (FIS) is the fastest and easiest way to use your PXI or PXI/SCXI combination systems right out of the box. Trained NI technicians install the software and hardware and configure the system to your specifications. NI extends the standard warranty by one year on hardware components (controllers, chassis, modules) purchased with FIS. To use FIS, simply configure your system online with ni.com/pxiadvisor.

Calibration Services

NI recognizes the need to maintain properly calibrated devices for high-accuracy measurements. We provide manual calibration procedures, services to recalibrate your products, and automated calibration software specifically designed for use by metrology laboratories. Visit ni.com/calibration.

Repair and Extended Warranty

NI provides complete repair services for our products. Express repair and advance replacement services are also available. We offer extended warranties to help you meet project life-cycle requirements. Visit ni.com/services.



ni.com • 800 813 3693

National Instruments • info@ni.com

