



*** spare part *** SIMATIC ET 200SP, Analog input module, AI Energy Meter 400 V AC ST, suitable for BU type D0, channel diagnostics

General information	
Product type designation	AI energy meter 400VAC ST
Firmware version	V3.0
usable BaseUnits	BU type D0
Product function	
• Voltage measurement	Yes
— with voltage transformer	No
• Current measurement	Yes
— without current transformer	No
— with current transformer	Yes
• Energy measurement	Yes
• Frequency measurement	Yes
• Power measurement	Yes
• Active power measurement	Yes
• Reactive power measurement	Yes
• I&M data	Yes; I&M0 to I&M3
• Isochronous mode	No
Engineering with	
• STEP 7 TIA Portal configurable/integrated from version	V13 SP1
• STEP 7 configurable/integrated from version	V5.5 SP4 and higher
• PROFIBUS from GSD version/GSD revision	GSD Revision 5
• PROFINET from GSD version/GSD revision	V2.3
Operating mode	
• cyclic measurement	Yes
• acyclic measurement	Yes
• Acyclic measured value access	Yes
• Fixed measured value sets	Yes
• Freely definable measured value sets	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Installation type/mounting	
Mounting position	any
Supply voltage	
Design of the power supply	Supply via voltage measurement channel L1
Rated value (AC)	100 - 240 V AC
permissible range, lower limit (AC)	90 V
permissible range, upper limit (AC)	264 V
Line frequency	
• permissible range, lower limit	47 Hz

• permissible range, upper limit	63 Hz
Power loss	
Power loss, typ.	0.6 W
Address area	
Address space per module	
• Address space per module, max.	44 byte; 32 byte input / 12 byte output
Hardware configuration	
Automatic encoding	
• Mechanical coding element	Yes
• Type of mechanical coding element	type C
Time of day	
Operating hours counter	
• present	No
Analog inputs	
Cycle time (all channels), typ.	50 ms; Time for consistent update of all measured and calculated values (cyclic und acyclic data)
Interrupts/diagnostics/status information	
Alarms	
• Diagnostic alarm	Yes
• Limit value alarm	No
• Hardware interrupt	No
Diagnostics indication LED	
• Monitoring of the supply voltage (PWR-LED)	Yes
• Channel status display	Yes; green LED
• for channel diagnostics	Yes; red Fn LED
• for module diagnostics	Yes; green/red DIAG LED
Integrated Functions	
Measuring functions	
• Measuring procedure for voltage measurement	TRMS
• Measuring procedure for current measurement	TRMS
• Type of measured value acquisition	seamless
• Curve shape of voltage	Sinusoidal or distorted
• Buffering of measured variables	No
• Parameter length	38 byte
• Bandwidth of measured value acquisition	2 kHz; Harmonics: 39 / 50 Hz, 32 / 60 Hz
Measuring range	
— Frequency measurement, min.	45 Hz
— Frequency measurement, max.	65 Hz
Measuring inputs for voltage	
— Measurable line voltage between phase and neutral conductor	230 V
— Measurable line voltage between the line conductors	400 V
— Measurable line voltage between phase and neutral conductor, min.	90 V
— Measurable line voltage between phase and neutral conductor, max.	264 V
— Measurable line voltage between the line conductors, min.	155 V
— Measurable line voltage between the line conductors, max.	460 V
— Internal resistance line conductor and neutral conductor	3.4 MΩ
— Power consumption per phase	20 mW
— Impulse voltage resistance 1,2/50μs	1 kV
— Measurement category for voltage measurement in accordance with IEC 61010-2-030	CAT II; CAT III in case of guaranteed protection level of 1.5 kV
Measuring inputs for current	
— measurable relative current (AC), min.	5 %; Relative to the secondary rated current; 1 A, 5 A
— measurable relative current (AC), max.	100 %; Relative to the secondary rated current; 1 A, 5 A
— Continuous current with AC, maximum permissible	5 A
— Apparent power consumption per phase for measuring range 5 A	0.6 VA

— Rated value short-time withstand current restricted to 1 s	100 A
— Input resistance measuring range 0 to 5 A	25 mΩ; At the terminal
— Surge strength	10 A; for 1 minute
— Zero point suppression	Parameterizable: 20 ... 250 mA, default 50 mA
Accuracy class according to IEC 61557-12	
— Measured variable voltage	0.5
— Measured variable current	0.5
— Measured variable apparent power	1
— Measured variable active power	1
— Measured variable reactive power	1
— Measured variable power factor	0.5
— Measured variable active energy	1
— Measured variable reactive energy	2
— Measured variable phase angle	±1 °; not covered by IEC 61557-12
— Measured variable frequency	0.05
Potential separation	
Potential separation channels	
• between the channels and backplane bus	Yes; 3 700V AC (type test) CAT III
Isolation	
Isolation tested with	2 300V AC for 1 min. (type test)
Ambient conditions	
Ambient temperature during operation	
• horizontal installation, min.	0 °C
• horizontal installation, max.	60 °C
• vertical installation, min.	0 °C
• vertical installation, max.	50 °C
Dimensions	
Width	20 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	45 g
Other	
Data for selecting a current transformer	
• Burden power current transformer x/1A, min.	As a function of cable length and cross section, see device manual
• Burden power current transformer x/5A, min.	As a function of cable length and cross section, see device manual

last modified: 12/28/2021 