



350VA 210W Standby UPS - 6 NEMA 5-15R Outlets, 120V, 50/60 Hz, 5-15P Plug, ENERGY STAR. Desktop/Wall

MODEL NUMBER: ECO350UPS











Compact desktop UPS provides battery backup support for your home/office network system, home theater or digital signage components.

Features

Energy-Saving 350VA/210W/120V Battery Backup for PCs, Home Theater and Digital Signage

The standby ECO350UPS UPS system provides reliable battery backup and AC power protection against blackouts, brownouts, overvoltages, surges and line noise that can damage valuable electronics or destroy data. The six-outlet 120V battery backup is ideal protection for your home office, media center or professional kiosk, security and small-business phone applications, including computers, routers, printers, HDTVs, Blu-ray players, game consoles, ATMs, security systems and digital signage equipment.

Allows Time to Back Up Critical Files During a Blackout

Backup support allows you to work through short power failures and gives you enough time to safely save files and shut down your system in case of a prolonged blackout. Backup time varies according to load, but the ECO350UPS should keep an energy-efficient desktop computer with small LCD monitor powered as long as 13 minutes. During normal operation, incoming utility power keeps the replaceable internal battery fully charged, so backup power will always be available.

6 NEMA 5-15R Outlets Protect Your Connected Components

Three 5-15R outlets provide battery backup and surge protection for your computer, monitor and other crucial component. The other three 5-15R outlets provide surge suppression only for printers, speakers and other desktop equipment regarded as non-essential during a blackout. Each outlet offers wide spacing to accommodate bulky transformer plugs.

ENERGY STAR-Certified to Help You Save Money and Protect the Environment

By meeting strict EPA efficiency guidelines, this ENERGY STAR-certified UPS system helps you save money and energy. An ECO power-saving option features two switched, surge-only ECO outlets that turn off automatically when the device connected to the Battery Backup Master Outlet is powered down or in sleep mode. These outlets are recommended for printers, desk lamps and other non-essential peripherals that don't need to be operational all the time.

316 Joules Fight Back Against Unexpected Power Surges

A 316-joule surge suppression rating protects connected components from the harmful effects of power surges.

HID-Compliant USB Port Allows for Automatic Saves and Shutdowns

Highlights

- Protects equipment against blackouts, brownouts, overvoltages, surges and line noise
- Keeps AC power running during blackouts to allow time for file saves and safe shutdown
- 6 NEMA 5-15R outlets power and protect PC, home theater or digital signage equipment
- Home-friendly alarm remains silent in backup mode, sounding only when imperative
- ENERGY STAR-certified to save electricity, lower costs, and protect the environment

Applications

- Protect your PC and other sensitive electronics against power surges, line noise, brownouts, overvoltages and blackouts
- Operate essential equipment during short-term power outages using battery backup power
- Shut down desktop PCs and other equipment without data loss during long-term power outages
- Turn off outlets connected to printers, desk lamps and other non-essential devices when not in use to save energy

Package Includes

- ECO350UPS 350VA 210W 120V Standby ECO UPS with 6 Outlets
- USB cable
- Owner's manual





This USB port connects the ECO350UPS to a computer running free downloadable PowerAlert® software to enable safe unattended file saves and system shutdown in case of a prolonged power failure. USB cable is included.

Combats Electromagnetic Interference That Can Harm Equipment

Various electromagnetic and radio sources found in virtually every home and business can cause disruptive interference on the AC line. Known as EMI (electromagnetic interference) and RFI (radio frequency interference), this line noise is a common cause of performance problems and can lead to incremental hardware damage, data corruption and audio/video transmission problems. The ECO350UPS incorporates technology that filters out disruptive line noise so that it won't affect your equipment.

Home-Friendly Alarm and Diagnostic LEDs Keep You Informed 24/7

The UPS remains silent in both line and battery backup modes. The alarm sounds only to warn you of a low battery, overload or fault condition. A front-panel green LED indicates operating mode, ECO mode and fault status.

Compact Housing Compatible with Easy Desktop or Wall-Mount Installation

The space-saving ABS housing fits on a desktop, shelf or anywhere else convenient to your workstation or home theater. Keyhole mounting tabs on the rear allow easy wall-mount installation. The five-foot power cord with NEMA 5-15P plug connects to any compatible AC outlet.

Specifications

OVERVIEW		
UPC Code	037332210982	
UPS Type	Standby	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	5A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
Input Circuit Breakers	5A	
UPS Input Cord Length (ft.)	5	
UPS Input Cord Length (m)	1.5	
Recommended Electrical Service	15A 120V	
Maximum Input Amps	5	
ОИТРИТ		
Output Capacity (VA)	350	
Output Capacity (kVA)	0.35	
Output Capacity (Watts)	210	
Output Capacity (kW)	0.21	
Output Capacity Details	2.9A @ 120V. (LINE MODE) 110%+/- 10% @ 5 minutes; (BATTERY MODE) 110% +/- 10% @ 5 seconds	
Nominal Voltage Details	120V sinusoidal in line mode and 120V PWM in battery mode	





Frequency Compatibility Details Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal. Output Voltage Regulation (Line double of the Company of t	Frequency Compatibility	50 / 60 Hz	
Output Voltage Regulation (Line Mode) 120V (+6%-12%) Mode) 120V (±0%) 120V (±10%) 120V (±1			
Mode) WeS Output Receptacles (Surge Suppression Only) Load Management Receptacles The ECO Energy-Saving option will automatically POWER OFF two designated ECO outlets when the device connected to the MASTER load-sensing outlet is turned off (after approximately 3 minutes): ECO outlets will interest only POWER OFF two designated ECO outlets will write the outlet of the MASTER load-sensing outlet is turned off (after approximately 3 minutes): ECO outlets will write the outlet of the MASTER load-sensing outlet begins consuming 15 output AC Waveform (AC Mode) Pure sine wave Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) 110V: 115V: 120V Output Receptacles (6) S-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 2 min. (210W) Runtime Half Load (min.) 8 min. (105W) Expandable Runtime No Do System Voltage (VDC) 12 Battery Roplacement Description 8 battery access door Battery Access Battery Access Battery access door Battery Access Battery Access Battery Access Battery Access Battery Access Battery Regulation Description Noutrage Regulation Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power office status and ECO mode affice status UPS comains ellent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions UPS dealine Suppression 1 in TELIDSL or Ethernet	Output Voltage Regulation (Line		
Suppression Only	Output Voltage Regulation (Battery Mode)	120V (±10%)	
connected to the MASTER load-sensing outlet is turned off (after approximately 3 minutes): ECO outlets will immediately POWER ON When the device connected to the MASTER load-sensing outlet begins consuming 15 watts or more (see manual) Output AC Waveform (AC Mode) Pure sine wave Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) Supported (6) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 2 min. (210W) Runtime Full Load (min.) 8 min. (105W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery access door Battery Replacement Description Replaceable Internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch Controls power offion status and ECO mode offion status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions UPS Dataline Suppression 1 line TEL/DSL or Ethernet	UPS Output Receptacles (Surge Suppression Only)	3 UPS outlets, 3 surge-only outlets	
Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported (6) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 2 min. (210W) Runtime Full Load (min.) 8 min. (105W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery access door Battery Access Battery Access Battery Access Battery Access Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status LED Indicators 1 status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION 1 line TEL/DSL or Ethernet	Load Management Receptacles	connected to the MASTER load-sensing outlet is turned off (after approximately 3 minutes); ECO outlets will immediately POWER ON when the device connected to the MASTER load-sensing outlet begins consuming 15	
Nominal Output Voltage(s) Nominal Output Voltage(s) Nominal Output Voltage(s) No Uutput Receptacles (6) 5-15R No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) Runtime Full Load (min.) Runtime Half Load (min.) Ru	Output AC Waveform (AC Mode)	Pure sine wave	
Supported Output Receptacles (6) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 2 min. (210W) Runtime Half Load (min.) 8 min. (105W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet		PWM sine wave	
Individually Controllable Load Banks BATTERY Battery Type	Nominal Output Voltage(s) Supported	110V; 115V; 120V	
BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 2 min. (210W) Runtime Half Load (min.) 8 min. (105W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 6.5 hours (10% to 90%) Battery Access Battery access door Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Output Receptacles	(6) 5-15R	
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 2 min. (210W) Runtime Half Load (min.) 8 min. (105W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Access Battery access door Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION 1 line TEL/DSL or Ethernet	Individually Controllable Load Banks	No	
Runtime Full Load (min.) 2 min. (210W) Runtime Half Load (min.) 8 min. (105W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery access door Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	BATTERY		
Runtime Half Load (min.) 8 min. (105W) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 6.5 hours (10% to 90%) Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switch Controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Battery Type	Valve Regulated Lead Acid (VRLA)	
Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery Recharge Rate (Included Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Runtime Full Load (min.)	2 min. (210W)	
Battery Recharge Rate (Included Battery access door Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Runtime Half Load (min.)	8 min. (105W)	
Battery Recharge Rate (Included Batteries) Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Expandable Runtime	No	
Battery Access Battery access door Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	DC System Voltage (VDC)	12	
Battery Replacement Description Replaceable internal batteries (see manual) VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Battery Recharge Rate (Included Batteries)	6.5 hours (10% to 90%)	
VOLTAGE REGULATION Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Battery Access	Battery access door	
Voltage Regulation Description Input voltage range of 90 to 145 USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Battery Replacement Description	Replaceable internal batteries (see manual)	
USER INTERFACE, ALERTS & CONTROLS Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	VOLTAGE REGULATION		
Switches Switch controls power off/on status and ECO mode off/on status Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Voltage Regulation Description	Input voltage range of 90 to 145	
Audible Alarm UPS remains silent in battery backup mode; Alarm sounds only to report low-battery, fault, overload and replace battery conditions 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	USER INTERFACE, ALERTS & CONTROLS		
battery conditions LED Indicators 1 Status LED reports operating mode, ECO mode and fault status SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Switches	Switch controls power off/on status and ECO mode off/on status	
SURGE / NOISE SUPPRESSION UPS Dataline Suppression 1 line TEL/DSL or Ethernet	Audible Alarm		
UPS Dataline Suppression 1 line TEL/DSL or Ethernet	LED Indicators	1 Status LED reports operating mode, ECO mode and fault status	
	SURGE / NOISE SUPPRESSION		
EMI / RFI AC Noise Suppression Yes	UPS Dataline Suppression	1 line TEL/DSL or Ethernet	
· · · · · · · · · · · · · · · · · · ·	EMI / RFI AC Noise Suppression	Yes	





AC Suppression Joule Rating	316	
AC Suppression Response Time	Instantaneous	
PHYSICAL		
Primary Form Factor	Desktop	
Installation Form Factors Supported with Included Accessories	Tower; Ultra-compact desktop; Wallmount	
Primary UPS Depth (mm)	185	
Primary UPS Height (mm)	105	
Primary UPS Width (mm)	110	
Shipping Dimensions (hwd / in.)	7.36 x 5.67 x 10.86	
Shipping Dimensions (hwd / cm)	18.69 x 14.40 x 27.58	
Shipping Weight (lbs.)	5.00	
Shipping Weight (kg)	2.27	
UPS Housing Material	ABS	
UPS Power Module Dimensions (hwd, cm)	10.49 x 11.00 x 18.49	
UPS Power Module Dimensions (hwd, in.)	4.13 x 4.33 x 7.28	
UPS Power Module Weight (kg)	1.80	
UPS Power Module Weight (lbs.)	3.96	
Unit Weight (lbs.)	5.000	
Unit Weight (kg)	2.27	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Storage Temperature Range	5° to 113°F (-15° to 45°C)	
Relative Humidity	0 to 90%, non-condensing	
AC Mode BTU / Hr. (Full Load)	13.1	
AC Mode Efficiency Rating (100% Load)	>98%	
Operating Elevation	0-6562 ft. (0-2000 m)	
COMMUNICATIONS		
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert	
Communications Cable	USB interface cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Network Management Card Description	Network management not supported	





Communications Interface	USB (HID enabled)	
LINE / BATTERY TRANSFER		
Transfer Time	6 milliseconds typical (10 milliseconds max)	
Low Voltage Transfer to Battery Power (Setpoint)	95	
High Voltage Transfer to Battery Power (Setpoint)	145	
FEATURES & SPECIFICATIONS		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Surge/noise protection	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS; Power saving auto-shutoff ECO outlets	
APPLICATIONS		
UPS Applications	Computer/Peripherals; Retail/Point of Sale; Hospitality	
STANDARDS & COMPLIANCE		
Product Certifications	RETIE (Colombia); CSA (Canada); NOM (Mexico); UL 1778	
Product Compliance	RoHS; ENERGY STAR Qualified; FCC Part 15 Class B (USA)	
WARRANTY & SUPPORT		
Product Warranty Period (U.S. & Canada)	3-year limited warranty	
Product Warranty Period (Latin America)	3-year limited warranty	
Product Warranty Period (International)	2-year limited warranty	
Product Warranty Period (Mexico)	3-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$100,000 Ultimate Lifetime Insurance	

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2025 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.