



Powering Business Worldwide

TRIPP LITE
SERIES

SmartPro 1440VA 1100W Line-Interactive Sine Wave UPS, AVR, 120V, 5 Outlets, Network Card Option, LCD, USB, 1U Rack/Tower

MODEL NUMBER: **SMC1500RT1U**



Provides complete battery backup and power protection for servers, switches and other in-rack IT equipment in small-to-mid-size networks.

Features

1440VA/1100W/120V Battery Backup for PC Networks, Security Systems or Digital Signage

This SmartPro® line-interactive UPS system with AVR provides reliable battery backup and AC power protection against blackouts, brownouts, surges and line noise that can damage valuable electronics or destroy data. The SMC1500RT1U is ideal protection for point-of-sale and kiosk applications, a small-business VoIP network or rack-mount equipment, such as servers and switches, in your server room or network closet.

Reliable Battery Backup Keeps You Operational Through Power Outages

The field-replaceable, hot-swappable internal battery provides eight minutes of support at half load (550W) and two minutes at full load (1100W), allowing you to work through short power failures and giving you enough time to safely save files and shut down your system in case of a prolonged blackout.

Optional WEBCARDLX Network Interface Offers 24/7 Remote Access for Monitoring and Control

The optional WEBCARDLX (sold separately) with the latest version of PowerAlert® Device Manager firmware (PADM20) provides enhanced remote management capabilities, including customizable dashboard graphs to fit user preferences. The PADM20 upgrade and PowerAlert Element Manager (PAEM) software form a powerful tool for expanding maintenance functions in large installations, including firmware update checks and backup and restoration of device configurations.

NEMA 5-15R Outlets Protect Your Connected Components

Five 5-15R outlets provide connected equipment with pure sine wave AC output during blackouts, overvoltages and severe brownout conditions. Power provided by these outlets is filtered to protect connected equipment against damaging surges and line noise.

Automatic Voltage Regulation (AVR) Corrects Low- and High-Voltage Conditions

AVR protects your equipment from incremental hardware damage, data loss and performance problems caused by brownouts. The SMC1500RT1U maintains regulated 120V nominal output during brownouts as low as 90V, while keeping the battery fully charged and ready to take over in case of power failure.

Premium Protection from EMI/RFI Line Noise Helps Your Equipment Perform Better

This UPS system filters out disruptive electromagnetic and radio frequency interference that can inflict hardware damage or data loss. This EMI/RFI filtering also helps your connected components perform

Highlights

- Protects equipment against blackouts, brownouts, transient surges and line noise
- Keeps AC power running during outages to allow time for file saves and safe shutdown
- Maintains continuous 120V nominal output during brownouts as low as 90V
- 5-15R outlets power and protect networking, telecom and other sensitive equipment
- Optional WEBCARDLX offers 24/7 remote access for enhanced real-time management

Package Includes

- 1440VA 1100W 120V Line-Interactive UPS with 5 Outlets
- USB cable
- EPO/ROO connector
- Rack-mounting hardware
- Owner's manual



Powering Business Worldwide

TRIPP LITE
SERIES

better and last longer.

Designed for High Efficiency to Help You Save Money and Protect the Environment

A 98% efficiency rating reduces BTU emissions, energy consumption and, ultimately, your energy costs.

Intuitive Front-Panel Interface for Convenient UPS Operation and Monitoring

The front-panel LCD features detailed UPS and site power status and operating data (including load, voltage and battery data) and multiple screens of configuration and setup options. LEDs indicate AC output availability and fault status. On-screen operational diagram offers an easy-to-grasp visual representation of line and battery modes.

Advanced Communications Ports Allow for Automatic Saves and Shutdowns

An HID-compliant USB port connects to a computer running free downloadable PowerAlert software to enable safe unattended shutdown in case of a prolonged power failure. The EPO/ROO port supports emergency shutdown in large facilities or remote On/Off capability. USB cable is included.

Versatile Installation Options

Hardware is included for mounting the UPS in just 1U of space in an EIA-standard 19-inch 4-post or 2-post rack. You can also adapt it for tower mounting using the included hardware. The six-foot power cord with NEMA 5-15P plug connects to a compatible AC outlet.

Specifications

OVERVIEW	
UPC Code	037332239358
UPS Type	Line-Interactive
INPUT	
Input Phase	Single-Phase
Rated input current (Maximum Load)	11.3A (100V); 12A (120V); 10.8A (127V)
Nominal Input Voltage(s) Supported	100V AC; 120V AC; 127V AC
UPS Input Connection Type	5-15P
Input Circuit Breakers	15A
UPS Input Cord Length (ft.)	6
UPS Input Cord Length (m)	1.8
Recommended Electrical Service	15A 120V
Maximum Input Amps	12
OUTPUT	
Output Capacity (VA)	1440
Output Capacity (kVA)	1.44
Output Capacity (Watts)	1100
Output Capacity (kW)	1.1
Output Capacity Details	1440 VA @ 120VAC and 127VAC, 100VAC: 1080 VA
Power Factor	0.76



Powering Business Worldwide

TRIPP LITE
SERIES

Nominal Voltage Details	120V sinusoidal in line mode and 120V sinusoidal in battery mode
Frequency Compatibility	50 / 60 Hz
Frequency Compatibility Details	Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal.
Output Voltage Regulation (Line Mode)	For 100V: 90VAC +/-5% -115VAC +/- 5% (78VAC +/- 5% -115VAC +/- 5%(@70VAC Input)) For 120V: 102VAC +/- 5% -139VAC +/- 5%, (78VAC +/- 5% -139VAC +/- 5%(@70VAC Input)), For 127V: 108VAC +/- 5% -145VAC +/- 5% (78VAC +/-5% -145VAC +/- 5% (@70VAC Input))
Output Voltage Regulation (Battery Mode)	-10%, +6%
Output AC Waveform (AC Mode)	Pure Sine wave
Output AC Waveform (Battery Mode)	Pure Sine wave
Nominal Output Voltage(s) Supported	120V
Output Receptacles	(5) 5-15R
Individually Controllable Load Banks	No
BATTERY	
Battery Type	Valve Regulated Lead Acid (VRLA)
Runtime Full Load (min.)	2 min. (1100W)
Runtime Half Load (min.)	8 min. (550W)
Expandable Runtime	No
DC System Voltage (VDC)	36
Battery Recharge Rate (Included Batteries)	6 Hours to 90%
Battery Access	Battery access panel
Internal UPS Replacement Battery Cartridge	RBC367-1U
Battery Replacement Description	Hot-swappable, user replaceable batteries
VOLTAGE REGULATION	
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with input voltage as low as 70V @ 120V/127V/100V (±5%). Input voltage range of 70V to 139V @ 100V; 70V to 162V @ 120V / 127V settings
Overvoltage Correction	Voltage reduction of 15% applies when input is 139V to 162V (120V), 145V to 162V (127V), 115V to 139V (100v); All voltage setpoints within ±5% tolerance
Undervoltage Correction	Voltage boost of 15% applies when input is 89V (HI Sensitivity) / 70V (LO sensitivity) to 102V @ 120V, 93V (HI sensitivity) / 70V (LO sensitivity) to 108V @ 127V, 80V (Hi sensitivity)/ 70V @ 100V; All voltage setpoints within ±5% tolerance
USER INTERFACE, ALERTS & CONTROLS	
Front Panel LCD Display	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, frequency, operating mode, alarm function and a variety of additional options (see manual)
Switches	ON button controls UPS ON, Cold-start, Self-test, and menu functions. OFF button controls unit off, fault clearance, and menu functions. Alarm/Enter button control audible alarm state and menu confirmation.
Audible Alarm	Audible alarm indicates UPS startup, power-failure, warnings, and low-battery conditions



Powering Business Worldwide

TRIPP LITE
SERIES

LED Indicators	2 LEDs indicate AC output status (Green); UPS fault (Solid Red)/ UPS abnormal conditions (Flashing Red).
SURGE / NOISE SUPPRESSION	
EMI / RFI AC Noise Suppression	Yes
AC Suppression Joule Rating	540
AC Suppression Response Time	Instantaneous
PHYSICAL	
Primary Form Factor	Rackmount; Tower
Rack Height	1U
Cooling Method	Fan
Installation Form Factors Supported with Included Accessories	2 post 19 inch rackmount; 2 post front mount; 4 post 19 inch rackmount; Tower
Maximum Device Depth (cm)	55.37
Maximum Device Depth (in.)	21.8
Maximum Device Depth (mm)	554
Minimum Required Rack Depth (cm)	63.50
Minimum Required Rack Depth (inches)	25
Primary UPS Depth (mm)	554
Primary UPS Height (mm)	44
Primary UPS Width (mm)	440
UPS Housing Material	Steel
UPS Power Module Weight (kg)	16.80
UPS Power Module Weight (lbs.)	37.037
Unit Weight (lbs.)	37.037
Unit Weight (kg)	16.80
Mounting Details	Included mounting brackets provide front-rail installation in 2 or 4 post racks, plus upright tower configurations
ENVIRONMENTAL	
Operating Temperature Range	32° to 104°F (0° to 40°C)
Storage Temperature Range	5° to 122°F (-15° to 50°C)
Relative Humidity	0 to 95%, non-condensing
AC Mode Efficiency Rating (100% Load)	98%
Operating Elevation	0-3280 ft. (0-1000 m)
Audible Noise	40 dBA maximum, front side 1m
COMMUNICATIONS	



Powering Business Worldwide

TRIPP LITE
SERIES

Network Management Cards	 WEBCARDLXE </td></tr><tr><td>Network Monitoring Port Description</td><td>Supports detailed monitoring of UPS and site power conditions</td></tr><tr><td>PowerAlert Software</td><td>For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert</td></tr><tr><td>Communications Cable</td><td>USB cabling included</td></tr><tr><td>WatchDog Compatibility</td><td>Supports Watchdog application, OS and hard-reboot restart options for remote applications</td></tr><tr><td>Network Management Card Description</td><td>Network management card optional</td></tr><tr><td>Communications Interface</td><td>(1) EPO (emergency power off); Slot for SNMP/Web interface; (1) USB (HID enabled)</td></tr><tr><td>Emergency Power Off (EPO)/Remote On-Off (ROO)</td><td>Yes</td></tr><tr><td>Emergency Power Off/Remote On-Off Details</td><td>Phoenix-style connection supports Emergency Power Off and Remote ON/OFF functions.</td></tr><tr><td data-cs="2" data-kind="parent">LINE / BATTERY TRANSFER</td><td data-kind="ghost"></td></tr><tr><td>Transfer Time</td><td>6-8 ms typical (< 10 ms max)</td></tr><tr><td>Low Voltage Transfer to Battery Power (Setpoint)</td><td>100V: 80VAC +/- 5% (HI sensitivity), 70VAC +/- 5%, (LO sensitivity), @120V: 89VAC +/- 5% (HI sensitivity), 70VAC+/- 5% (LO sensitivity), @127V: 93VAC+/- 5%, (HI sensitivity), 70VAC+/- 5%, (LO sensitivity)</td></tr><tr><td>High Voltage Transfer to Battery Power (Setpoint)</td><td>162 VAC (120VAC/127VAC INPUT), 139 VAC (100VAC INPUT) +/- 5%</td></tr><tr><td data-cs="2" data-kind="parent">FEATURES & SPECIFICATIONS</td><td data-kind="ghost"></td></tr><tr><td>Cold Start (Startup in Battery Mode During a Power Failure)</td><td>Cold-start operation supported</td></tr><tr><td>High Availability UPS Features</td><td>Auto Probe Monitoring (requires WEBCARDLXE); Automatic Voltage Regulation (AVR); Hot swappable batteries; Remote management; Surge/noise protection</td></tr><tr><td>Grounding Details</td><td>Back panel grounding lug</td></tr><tr><td data-cs="2" data-kind="parent">APPLICATIONS</td><td data-kind="ghost"></td></tr><tr><td>UPS Applications</td><td>High-End Desktop/Small Network; Retail/Point of Sale; Hospitality</td></tr><tr><td data-cs="2" data-kind="parent">STANDARDS & COMPLIANCE</td><td data-kind="ghost"></td></tr><tr><td>Product Certifications</td><td>CSA (Canada); UL 1778</td></tr><tr><td>Product Compliance</td><td>ENERGY STAR Qualified; FCC Part 15 Class B (USA)</td></tr><tr><td data-cs="2" data-kind="parent">WARRANTY & SUPPORT</td><td data-kind="ghost"></td></tr><tr><td>Product Warranty Period (Worldwide)</td><td>2-year warranty, 3 year with registration. Note: Registration is required for 3-year warranty.</td></tr><tr><td>Extended Warranties</td><td>1-year and 2-year extensions available</td></tr><tr><td>Connected Equipment Insurance (U.S., Canada & Puerto Rico)</td><td>\$250,000 Ultimate Lifetime Insurance </td></tr></table></div><div data-bbox="485 974 511 985" data-label="Page-Footer"><p>5 / 6</p></div>
--------------------------	---



Powering Business Worldwide

TRIPP LITE
SERIES

1000 Eaton Boulevard
Cleveland, OH 44122
United States
<https://tripplite.eaton.com>

© 2025 Eaton. All Rights Reserved.
Eaton is a registered trademark. All other trademarks
are the property of their respective owners.