



SmartOnline 200-240V 10kVA 9kW Double-Conversion UPS, 6U, Extended Run, Network Card Slot, USB, DB9, Bypass Switch,C19

MODEL NUMBER: SU10000RT3UG











Description

The SU10000RT3UG 10,000VA/9000W online, double-conversion UPS system offers complete power protection for critical network applications. This system delivers online, double-conversion UPS protection with zero transfer time, suitable for advanced networking applications. Fault-tolerant auto-bypass prevents unexpected service interruptions during UPS overload or internal fault conditions. Included detachable PDU with manual bypass switch enables hot-swappable replacement of entire UPS power module with no interruption to connected equipment. Enhanced availability, fault tolerance and simple hot-swap replacement options make this UPS ideal for advanced networking applications in data centers, computer rooms, network closets and rugged industrial locations.

Features

- SU10000RT3UG 10kVA / 10,000VA / 9000 watt on-line, double-conversion UPS system in 6U total rack/tower configuration (3U UPS power module and 3U external battery pack)
- Detachable PDU with manual bypass switch enables hot-swappable UPS power module replacement with no interruption in output power to connected networking equipment
- · Fault tolerant electronic bypass maintains utility output during a variety of UPS fault conditions
- Hardwire input; 6 C19 outlets
- Maximum installed rack depth of only 32.5 in. / 82.6cm
- Full-time active power conditioning provides clean, continuous dual-conversion AC output free of voltage fluctuations, power interruptions and line noise
- Double-conversion operation converts raw input from AC to DC, then resynthesizes output power back
 to perfect sine wave AC with enhanced protection from harmonic distortion, fast electrical impulses and
 other hard-to-solve power problems not addressed by other UPS types
- Maintains full-time sine wave output within 2% of selectable 200/208/220/230/240V nominal during brownouts as low 100V and overvoltages as high as 300V
- Supports 50/60 Hz operation for worldwide frequency compatibility
- Expandable runtime is supported with optional BP240V10RT3U; BP240V787C-1PH external battery packs
- Some external battery configurations require the use of External Battery Configuration Software (see manual)
- Intelligent battery management system with temperature-compensated charging extends battery life

Highlights

- 10kVA / 10,000VA / 9000W online double-conversion UPS; 0.9 power factor; Extended runtime; Economy mode option
- 6U rack/tower configuration with hot-swappable power and battery modules; Maintenance bypass switch included
- Add optional WEBCARDLX with latest version of PADM20 for enhanced remote management
- Hardwire 200-240V 50/60Hz input (3 wire); C19 outlets; Configurable for 200/208/220/230/240V output

Package Includes

- SU10000RT3UPM 3U UPS power module
- BP240V10RT3U external battery pack
- SUPDMB710IEC Detachable PDU with manual bypass switch
- Four post compatible rack rail kit (2 sets)
- USB, DB9 and EPO Cabling
- Instruction manual





- Highly efficient operation in optional economy mode significantly reduces BTU heat output and operating energy costs
- Battery independent restart ensures automatic UPS power-up without user interaction after lengthy power outages, even when batteries are expired and require replacement
- USB & Serial ports enable data-saving unattended shutdown when used with PowerAlert software, available via FREE download from tripplite.eaton.com/products/power-alert
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and macOS
- Compatible UPS management card options TLNETCARD, WEBCARDLX, SNMPWEBCARD, MODBUSCARD and RELAYIOCARD support a wide variety of UPS control and monitoring capabilities
- Optional WEBCARDLX (sold separately) with the latest version of PowerAlert Device Manager firmware (PADM20) provides enhanced remote management capabilities
- PADM20 and PowerAlert Element Manager (PAEM) form a powerful tool for expanding maintenance functions in large installations, including firmware update checks and backup and restoration of device configurations
- Optional RELAYIOMINI interface module offers three configurable hard contact closure outputs for custom event notification (requires removal of USB interface module)
- Supports Emergency Power Off (EPO) via built-in interface
- Included rail kit supports 6U 19-inch rack-mount installation in 4-post racks
- Optional 2POSTRMKITHD supports installation in 2-post 19-inch racks
- Front panel LEDs and LCD readout with scroll controls and password option supports visual monitoring
 of all major UPS functions and advanced UPS settings for charge level, nominal voltage selection,
 frequency conversion and other operational parameters
- LED / LCD display panel rotates for viewing in rack-mount or tower configurations
- Network-grade AC surge and noise suppression
- Industrial mode option (factory preset) enables supports high-current startup loads by momentarily switching to bypass mode in response to short duration overload conditions
- Frequency conversion mode enables conversion of 60 Hz to 50Hz or 50Hz to 60 Hz (no de-rating)
- External battery packs are field replaceable and hot swappable

Specifications

OVERVIEW		
UPC Code	037332146373	
UPS Type	On-Line	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	56.1A (200V), 54A (208V), 51A (220V), 48.8A (230V), 46.8A (240V)	
Nominal Input Voltage(s) Supported	200V AC; 208V AC; 220V AC; 230V AC; 240V AC	
UPS Input Connection Type	Hardwire	
UPS Input Connection Description	Supports North American 208/240V input (L1,L2,G) and International 230/220/240V (L,N,PE) input wiring	
Recommended Electrical Service	60A	
Voltage Compatibility (VAC)	200; 208; 230; 240; 220	
ОИТРИТ		





Power Factor 0,9 Crest Factor 3:1 Nominal Voltage Details Voltage selection Frequency Compatibility 50 / 60 Hz; Supported Voltage Regulation (Line Mode) +/- 2% Output Voltage Regulation (Line Mode) +/- 10% Output Voltage Regulation (Battery Mode) +/- 2% Output Voltage Regulation (Battery Mode) +/- 2% Output Circuit Breakers 20A double-poor 20	105% load continuously in double conversion mode, 106 to 125% for 1 minute, 126% to 150% for 30 s over 150% trigger immediate bypass mode operation to support loads directly from mains power; sion mode is automatically restored as load levels are reduced to 95% or less on via front panel LCD interface sports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to 60Hz (No de-rating); Output frequency regulation +/- 0.05Hz (free running)
Output Capacity (Watts) Output Capacity (kW) Output Capacity Details Supports up to seconds; Load Double convertion of Double Conver	s over 150% trigger immediate bypass mode operation to support loads directly from mains power; sion mode is automatically restored as load levels are reduced to 95% or less on via front panel LCD interface oports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Output Capacity (kW) Output Capacity Details Supports up to seconds; Load Double conver Power Factor O,9 Crest Factor Nominal Voltage Details Frequency Compatibility Frequency Compatibility Frequency Compatibility Details Output frequer 50Hz or 50Hz Output Voltage Regulation (Line Mode) Output Voltage Regulation (Battery Mode) Output Voltage Regulation (Battery Mode) Output Circuit Breakers Output AC Waveform (AC Mode) Pure Sine wav Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported Output Receptacles (6) C19 Individually Controllable Load Banks No BATTERY Battery Type Valve Regulate Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime Yes External Battery Pack Compatibility BP240V10RT3	s over 150% trigger immediate bypass mode operation to support loads directly from mains power; sion mode is automatically restored as load levels are reduced to 95% or less on via front panel LCD interface oports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Output Capacity Details Power Factor O,9 Crest Factor Nominal Voltage Details Frequency Compatibility Frequency Compatibility Details Output Frequency Compatibility Details Output Voltage Regulation (Line Mode) Output Voltage Regulation (Line Mode) Output Voltage Regulation (Battery Mode) Output Voltage Regulation (Battery Mode) Output Circuit Breakers Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported Output Receptacles (6) C19 Individually Controllable Load Banks No BATTERY Battery Type Valve Regulation Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime Yes External Battery Pack Compatibility BP240V10RT3	s over 150% trigger immediate bypass mode operation to support loads directly from mains power; sion mode is automatically restored as load levels are reduced to 95% or less on via front panel LCD interface oports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Power Factor 0,9 Crest Factor 3:1 Nominal Voltage Details Voltage selection 50 / 60 Hz; Supported Pourput Voltage Regulation (Line Mode) +/- 2% Output Voltage Regulation (Battery Mode) +/- 2% Output Voltage Regulation (Battery Mode) +/- 2% Output Voltage Regulation (Battery Mode) Pure Sine wave Mode) Pure Sine wave Pourput AC Waveform (AC Mode) Pure Sine wave	s over 150% trigger immediate bypass mode operation to support loads directly from mains power; sion mode is automatically restored as load levels are reduced to 95% or less on via front panel LCD interface oports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Crest Factor 3:1 Nominal Voltage Details Voltage selection Frequency Compatibility 50 / 60 Hz; Superior Frequency Compatibility Details Output frequency SoHz or 50Hz	oports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Nominal Voltage Details Frequency Compatibility Frequency Compatibility Details Output frequency Compatibility Details Output Voltage Regulation (Line Mode) Output Voltage Regulation (Economy Line Mode) Output Voltage Regulation (Battery Mode) Output Voltage Regulation (Battery Mode) Output Circuit Breakers Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) Pure Sine wave Mode) Nominal Output Voltage(s) Supported Output Receptacles Individually Controllable Load Banks BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime Yes External Battery Pack Compatibility BP240V10RT3	oports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Frequency Compatibility Frequency Compatibility Details Output Frequency Compatibility Details Output Voltage Regulation (Line Mode) Output Voltage Regulation (Economy Line Mode) Output Voltage Regulation (Battery Mode) Output Voltage Regulation (Battery Mode) Output Circuit Breakers Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) Pure Sine wave Sine wave Supported Output Receptacles Output Receptacles Individually Controllable Load Banks BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility Output Receptacles BP240V10RT3	oports 50 to 60 Hz and 60 to 50 Hz conversion cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Frequency Compatibility Details Output frequency Compatibility Details Output Voltage Regulation (Line Mode) Output Voltage Regulation (Economy Line Mode) Output Voltage Regulation (Battery Mode) Output Circuit Breakers Output Circuit Breakers Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) Pure Sine wave Sine wave Supported Output Receptacles Output Receptacles Individually Controllable Load Banks BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility Output Receptacles BP240V10RT3	cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to
Output Voltage Regulation (Line Mode) +/- 2% Output Voltage Regulation (Economy Line Mode) +/- 10% Output Voltage Regulation (Battery Mode) +/- 2% Output Voltage Regulation (Battery Mode) +/- 2% Output Circuit Breakers 20A double-po Output AC Waveform (AC Mode) Pure Sine wave M	cy matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to o 60Hz (No de-rating); Output frequency regulation +/- 0.05Hz (free running)
Mode) Output Voltage Regulation (Economy Line Mode) Output Voltage Regulation (Battery Mode) Output Circuit Breakers Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) Pure Sine waveform (Battery Mode) Nominal Output Voltage(s) Supported Output Receptacles (6) C19 Individually Controllable Load Banks Pattery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility ##- 2% ##- 10% ##- 10% ##- 10% ##- 10% ##- 2% ##- 10% ##- 2% ##- 10% ##- 2% ##- 10% ##- 2% ##- 2% ##- 2% ##- 2% ##- 10% ##- 2% ##- 2% ##- 2% ##- 2% ##- 2% ##- 2% ##- 2% ##- 2% ##- 2% ##- 2% ##- 10% ##- 2% ##- 2% ##- 2% ##- 10% ##- 2% ##-	
(Economy Line Mode) Output Voltage Regulation (Battery Mode) Output Circuit Breakers Output AC Waveform (AC Mode) Pure Sine wav Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported Output Receptacles Individually Controllable Load Banks Pattery Battery Type Valve Regulate Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility Pure Sine wav 200V; 208V; 2: 4.3 min. (9000) 12.5 min. (450) Pure Sine wav 200V; 208V; 2: 200	
Mode) Output Circuit Breakers Output AC Waveform (AC Mode) Pure Sine wav Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported Output Receptacles Individually Controllable Load Banks BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility 20A double-po Pure Sine wav 200V; 208V; 22 200V; 208V; 208V; 208V; 208V;	
Output AC Waveform (AC Mode) Pure Sine wav Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported Output Receptacles Individually Controllable Load Banks BATTERY Battery Type Valve Regulate Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility Pure Sine wav 200V; 208V; 2: 400 C19 No 120 C19 No 120 C19 12	
Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported Output Receptacles Individually Controllable Load Banks BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility Pure Sine wav 200V; 208V; 25 200V; 208V;	le (x6) protects 1 C19 outlet each
Nominal Output Voltage(s) Supported Output Receptacles Individually Controllable Load Banks BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility Pure Sirie wav 200V; 208V; 22 (6) C19 Valve Regulate 4.3 min. (9000) 12.5 min. (450) Expandable Runtime Yes External Battery Pack Compatibility	e
Output Receptacles (6) C19 Individually Controllable Load Banks No BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime Yes External Battery Pack Compatibility Public Compact Service Control Compact Service	9
Individually Controllable Load Banks No BATTERY Battery Type Valve Regulate Runtime Full Load (min.) 4.3 min. (9000) Runtime Half Load (min.) 12.5 min. (450) Expandable Runtime Yes External Battery Pack Compatibility BP240V10RT3	20V; 230V; 240V
BATTERY Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility Yes BP240V10RT3	
Battery Type Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime Yes External Battery Pack Compatibility Valve Regulate 4.3 min. (9000 12.5 min. (450)	
Runtime Full Load (min.) Runtime Half Load (min.) Expandable Runtime External Battery Pack Compatibility 4.3 min. (9000 12.5 min. (450) Yes External Battery Pack Compatibility	
Runtime Half Load (min.) Expandable Runtime Yes External Battery Pack Compatibility BP240V10RT3	ed Lead Acid (VRLA)
Expandable Runtime Yes External Battery Pack Compatibility BP240V10RT3	N)
External Battery Pack Compatibility BP240V10RT3	DW)
DC System Voltage (VDC) 240	U; BP240V787C-1PH
20 Cyclem Vollage (V2C)	
Battery Recharge Rate (Included Batteries) Less than 8 ho	urs from 10% to 90% (typical, full load discharge)
Battery Replacement Description Hot-swappable	
VOLTAGE REGULATION	, user replaceable external battery packs
Voltage Regulation Description 2% output voltage	, user replaceable external battery packs
Overvoltage Correction Corrects overv	age regulation in standard online, double-conversion mode





Undervoltage Correction	Corrects undervoltages as low as 100V
HEED INTEDEACE ALEDTS & CON-	TROLS
USER INTERFACE, ALERTS & CON	IROLS
Front Panel LCD Display	Selectable LCD display with scroll and selection buttons enables UPS control and detailed monitoring options; LED/LCD panel rotates for viewing in rack/tower formats; LCD Display supports ENGLISH, FRENCH, GERMAN, ITALIAN, SPANISH and PORTUGUESE (see manual)
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation; 2 additional switches support set and execute scrolling LCD functions; bundled PDU includes bypass switch to enable hot-swap UPS power module replacement
Alarm Cancel Operation	Alarm cancel switch
Audible Alarm	Unique audible alarms for all major UPS, environmental and power conditions (see manual)
LED Indicators	6 LEDs indicate line power, online mode, economy/bypass mode, on-battery, charger and AC output status; LCD screen offers additional information and control options
SURGE / NOISE SUPPRESSION	
UPS AC Suppression Joule Rating	2565
UPS AC Suppression Response Time	Instantaneous
EMI / RFI AC Noise Suppression	Yes
PHYSICAL	
Primary Form Factor	Rackmount
Rack Height	6U
Cooling Method	Fan
Included Battery Pack Dimensions (hwd / in.)	5.25 x 17.5 x 25
Included Battery Pack Weight (lbs.)	158.7
Included Battery Pack Weight (kg)	71.99
Included Mounting Accessory Description	2 sets of adjustable 4 post rack rails included
Installation Form Factors Supported with Included Accessories	4 post 19 inch rackmount
Installation Form Factors Supported with Optional Accessories	2 post rackmount (2POSTRMKITHD); Tower (2-9USTAND)
Maximum Device Depth (cm)	95.25
Maximum Device Depth (in.)	37.5
Maximum Device Depth (mm)	953
Minimum Required Rack Depth (cm)	83.82
Minimum Required Rack Depth (inches)	33
Optional Mounting Accessory Notes	2 sets of 2POSTRMKITHD required for 2 post rackmount installation (supports up to 9U in tower format)





Primary UPS Depth (mm)	656	
Primary UPS Height (mm)	131	
Primary UPS Width (mm)	445	
Shipping Dimensions (hwd / in.)	32.00 x 26.00 x 41.00	
Shipping Dimensions (hwd / cm)	81.28 x 66.04 x 104.14	
Shipping Weight (lbs.)	310.00	
Shipping Weight (kg)	140.61	
Unit Dimension Details	Includes 3U UPS/power module, 3U external battery pack plus SUPDMB710IEC PDU with bypass; MAXIMUM DEVICE DEPTH specification refers to the whole UPS installed depth with bypass PDU installed	
UPS Housing Material	Steel	
UPS Power Module Dimensions (hwd, cm)	13.06 x 44.45 x 65.58	
UPS Power Module Dimensions (hwd, in.)	5.14 x 17.5 x 25.82	
UPS Power Module Weight (kg)	19.50	
UPS Power Module Weight (lbs.)	43	
Unit Dimensions (hwd / in.)	10.500 x 17.500 x 35.000	
Unit Weight (lbs.)	210.73	
Unit Weight (kg)	95.59	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Storage Temperature Range	5° to 122°F (-15° to 50°C)	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	3415	
AC Economy Mode BTU / Hr. (Full Load)	1280	
AC Mode Efficiency Rating (100% Load)	91%	
AC Economy Mode Efficiency Rating (100% Load)	96%	
Online Mode Heat Dissipation (BTU/Hr) @ Full Load	3415	
Battery Mode Heat Dissipation (BTU/Hr) @ Full Load	4593	
Operating Elevation	0-10000 ft. (0-3000 m)	
Audible Noise	60 dBA at front side 1 meter	
COMMUNICATIONS		





TLNETCARD ; WEBCARDLXE ; MODBUSCARD ; RELAYIOCARD
Additional contact closure support with optional RELAYIOCARD and RELAYIOMINI interface cards. RELAYIOMINI installation requires removal of panel containing USB ports
For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert
USB, DB9 serial and EPO cables included
Supports Watchdog application, OS and hard-reboot restart options for remote applications
Network management card optional
DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface; USB (HID enabled)
No transfer time (0 ms.) in online, double-conversion mode
8 ms. typical power failure response in optional economy mode
100V
300V
Cold-start operation supported
Optional economy mode enables high efficiency bypass operation with a maximum output voltage variation of +/- 10%. Double conversion mode is automatically restored as mains voltage varies beyond +/-10% with less than 1 millisecond transfer time between modes.
Auto Probe Monitoring (requires WEBCARDLXE); Automatic inverter bypass; Hot swappable UPS power module; Hot swappable batteries; Manual bypass switch; Remote management; Surge/noise protection; Zero transfer time
High efficiency economy mode operation; Schedulable daily hours of economy mode operation
Mission Critical Applications
IEC 61000; CSA (Canada); NOM (Mexico); UL 1778
RoHS; CE (Europe); FCC Part 15 Class A (USA)
RoHS; CE (Europe); FCC Part 15 Class A (USA)
RoHS; CE (Europe); FCC Part 15 Class A (USA) 2-year limited warranty





1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2025 Eaton. All Rights Reserved.

Eaton is a registered trademark. All other trademarks are the property of their respective owners.