

Low Noise Amplifier Operating From 1.2 GHz to 1.4 GHz with 35 dB Gain, 15 dBm P1dB and SMA

The FMAM1024 is an L-band high gain low noise coaxial amplifier operating in the 1.2 to 1.4 GHz frequency range. The low noise amplifier offers 15 dBm min of P1db and 35 dB typical small signal gain with gain flatness of ± 0.75 dB typical. This excellent technical performance is achieved through the use of hybrid MIC design and advanced GaAs PHEMT devices. The low noise amplifier requires typically a +12V DC power supply. The connectorized SMA module is unconditionally stable and includes built-in voltage regulation. The amplifier operates over the temperature range of -40°C and +75°C.

Electrical Specifications (TA = +25°C , DC Voltage = 12Volts , DC Current = 180mA)

Description	Min	Typ	Max	Unit
Frequency Range	1.2		1.4	GHz
Small Signal Gain	35			dB
Gain Flatness		± 0.75	± 1	dB
Output at 1 dB Compression Point	+15			dBm
Input VSWR			2:1	
Output VSWR			2:1	
Operating DC Voltage	10.8	12	13.2	Volts
Operating DC Current		180		mA
Operating Temperature Range	-40		+75	°C

Mechanical Specifications

Size	
Length	2.32 in [58.93 mm]
Width	2.32 in [58.93 mm]
Height	0.71 in [18.03 mm]
Input Connector	SMA Female
Output Connector	SMA Female

Environmental Specifications

Temperature	
Operating Range	-40 to +75 deg C

Compliance Certifications (visit www.FairviewMicrowave.com for current document)

RoHS Compliant	Yes
----------------	-----

Plotted and Other Data

- Notes:
- Values at 25 °C, sea level
 - ESD Sensitive Material, Transport material in Approved ESD bags. Handle only in approved ESD Workstation.



Features:



- 1.2 GHz to 1.4 GHz Frequency Range
- P1dB: 15 dBm min
- Small Signal Gain: 35 dB min
- Gain Flatness: ± 0.75 dB typical
- Noise Figure: 1.5 dB typ
- 50 Ohm Input and Output Matched
- Unconditionally Stable
- Regulated Supply & Bias Sequencing

Applications:

- L-band Military Radar
- Commercial Air Traffic Control
- Weather & Earth Observation Satellites
- Radar & Communication Systems
- High Gain Low Noise Amplifier

Fairview Microwave
1130 Junction Dr. #100
Allen, TX 75013
Tel: 1-800-715-4396 / (972) 649-6678
Fax: (972) 649-6689
www.fairviewmicrowave.com
sales@fairviewmicrowave.com

Typical Performance Data





Low Noise Amplifier Operating From 1.2 GHz to 1.4 GHz with 35 dB Gain, 15 dBm P1dB and SMA from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Allen, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: [Low Noise Amplifier Operating From 1.2 GHz to 1.4 GHz with 35 dB Gain, 15 dBm P1dB and SMA FMAM1024](#)

URL: <http://www.fairviewmicrowave.com/low-noise-amplifier-35db-fmam1024-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.





NOTE:
HEAT SINK REQUIRED FOR PROPER OPERATION,
UNIT IS COOLED BY CONDUCTING TO HEAT SINK.

FAIRVIEW MICROWAVE INC. ALLEN, TX 75013 WWW.FAIRVIEWMICROWAVE.COM		NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm].			
TITLE Low Noise Amplifier Operating From 1.2 GHz to 1.4 GHz with 35 dB Gain, 15 dBm P1dB and SMA		DWG NO FMAM1024		CAGE CODE 3FKR5	
		CAD FILE 021715	SHEET	SCALE N/A	SIZE A