

## LDP-CW 20-50

Rev. 1905

## Fully digital cw Driver for High Power Laser Diodes






Figure: Soft Start, Current monitor output, scale: 10A/Div

## **Product Description**

The LDP-CW 20-50 is a very affordable, compact and efficient current supply for an output power up to 1 kW.

The capability ranges from continuous output current to analog modulated waveforms like sinusoidal, rectangular or triangular. The modulation is limited usually by the load inductance.

Intended field of application are laser soldering and welding as well as generic surface treatment and show lasers.

The innovative current regulation concept of the LDP-CW 20-50 produces, compared to the commonly used linear regulation concept, considerably less losses. Hence, only one supply voltage is needed for the control logic and the power stage. The current consumption drawn from the power supply only needs to cover the average laser power and is typically much less than 20 A.

Output current: 1 .. 20 ACompliance voltage: 0 .. 50 V

Output power: 1 kWCoverage of cw range

Analog modulation

• Half brick size (35 cm<sup>2</sup>)

• Several protective features

High efficiency

## Technical Data\*

Output current
Max. compliance voltage
Current ripple
Ripple frequency
Current overshoot
Analog modulation (10
A<sub>pp</sub>)
Current settling time
(full-scale)
Current setting input
Supply voltage

Max. power dissipation Dimensions in mm

Weight
Operating temperature

1 .. 20 A 1 .. 50 V < 1 % > 1 MHz

Refer to manual\*\* Refer to manual\*\*

Refer to manual\*\*

Analog or digital
12 .. 55 V DC (min. 5 V
above laser diode voltage)
< 45 W
60.9 x 57.8 x 29
Half brick size
194 g
0 to +55 °C

\* Specifications measured with a fast recovery diode instead of a laser diode. Technical data is subject to change without further notice.

\*\* Actual values depend on hardware setup

Designed to shield your laser diode from damage, the LDP-CW 20-50 features a number of powerful protective safeguards:

- Innovative current regulation concept actively prevents laser diode from overshoots and overcurrent
- Integrated Soft Start
- Overtemperature shutdown
- Enable/Disable input
- Driver status output
- Protection of the laser diode against reverse currents

Optional Accessories: LDP-C BOB PLB-21

PicoLAS GmbH Burgstr. 2 52146 Würselen Germany

Phone: +49 (0)2405 64594 60 Fax: +49 (0)2405 64594 61 E-mail: sales@picolas.de Web: www.picolas.de