



SANYO Semiconductors

DATA SHEET

An ON Semiconductor Company

2SB1121 / ~~2SD1621~~ — PNP / ~~NPN~~ Epitaxial Planar Silicon Transistors

High-Current Driver Applications

Applications

- Voltage regulators, relay drivers, lamp drivers, electrical equipment.

Features

- Adoption of FBET, MBIT processes.
- Low collector-to-emitter saturation voltage.
- Large current capacity and wide ASO.
- Fast switching speed.
- Ultrasmall size making it easy to provide high-density, small-sized hybrid IC's.

Specifications () : 2SB1121

Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Conditions	Ratings	Unit
Collector-to-Base Voltage	VCBO		(-) 30	V
Collector-to-Emitter Voltage	VCEO		(-) 25	V
Emitter-to-Base Voltage	VEBO		(-) 6	V
Collector Current	IC		(-) 2	A
Collector Current (Pulse)	ICP		(-) 5	A
Collector Dissipation	PC		500	mW
		Mounted on a ceramic board (250mm \times 0.8mm)	1.3	W
Junction Temperature	Tj		150	°C
Storage Temperature	Tstg		-55 to $+150$	°C

Marking 2SB1121 : BD

~~2SD1621 : DD~~

■ Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment (home appliances, AV equipment, communication device, office equipment, industrial equipment etc.). The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for applications outside the standard applications of our customer who is considering such use and/or outside the scope of our intended standard applications, please consult with us prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.

■ Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

SANYO Semiconductor Co., Ltd.

<http://semicon.sanyo.com/en/network>

Electrical Characteristics at Ta=25°C

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Collector Cutoff Current	ICBO	VCB=(-)20V, IE=0A			(-)0.1	μA
Emitter Cutoff Current	IEBO	VEB=(-)4V, IC=0A			(-)0.1	μA
DC Current Gain	hFE1	VCE=(-)2V, IC=(-)100mA	100*		560*	
	hFE2	VCE=(-)2V, IC=(-)1.5A	65			
Gain-Bandwidth Product	fT	VCE=(-)10V, IC=(-)50mA		150		MHz
Output Capacitance	Cob	VCB=(-)10V, f=1MHz		(32)19		pF
Collector-to-Emitter Saturation Voltage	VCE(sat)	IC=(-)1.5A, IB=(-)75mA		(-0.35)0.18	(-0.6)0.4	V
Base-to-Emitter Saturation Voltage	VBE(sat)	IC=(-)1.5A, IB=(-)75mA		(-)0.85	(-)1.2	V
Collector-to-Base Breakdown Voltage	V(BR)CBO	IC=(-)10μA, IE=0A	(-)30			V
Collector-to-Emitter Breakdown Voltage	V(BR)CEO	IC=(-)1mA, RBE=∞	(-)25			V
Emitter-to-Base Breakdown Voltage	V(BR)EBO	IE=(-)10μA, IC=0A	(-)6			V
Turn-ON Time	ton	See specified Test Circuit.		(60)60		ns
Storage Time	tstg	See specified Test Circuit.		(350)550		ns
Fall Time	tf	See specified Test Circuit.		(25)25		ns


*: The 2SB1121 / 2SD1621 are classified by 100mA hFE as follows:

Rank	R	S	T	U
hFE	100 to 200	140 to 280	200 to 400	280 to 560


Package Dimensions

unit : mm (typ)

7007B-004












Switching Time Test Circuit



IC=20IB1= -20IB2=500mA
(For PNP, the polarity is reversed)

2SB1121 / 2SD1621





- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co.,Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellectual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of March, 2010. Specifications and information herein are subject to change without notice.