



## Product Description

This is a simple evaluation board that allows quick evaluation of the performance of the 3SM222KMB1HA-P bottom port digital output omnidirectional microphones. The evaluation board has a 5-pin for access to all microphone pins.


- The evaluation board is equipped with a digital PDM output microphone and a 0.1μF supply bypass capacitor.
- Bottom Port PDM microphone has already mounted to evaluation board.

## Microphone Specifications

Typical test conditions are  $T_A = 23\text{ }^{\circ}\text{C}$ ,  $V_{DD} = 1.8\text{V}$  and  $R.H. = 50\%$  measured in a pressure chamber test setup. All voltages refer to GND node

Microphone Parameters	Typical Specification
Microphone Part Number	3SM222KMB1HA-P
Supply Voltage	1.6 to 3.6V
Current Consumption	550μA( $V_{dd}=1.8\text{V}$ ) ; 850μA( $V_{dd}=3.6\text{V}$ )
Interface	PDM
Sensitivity	-26 dBFS (1KHz, 94dBSPL)
Signal to Noise Ratio	64 dBA
Low Frequency Roll-off	35Hz (-3dB relative to 1KHz)
Acoustic Overload Point	120 dBSPL (10% THD@1KHz)
Clock Frequency	1.0 to 4.8 MHz
Package Dimensions	3.50mm x 2.65mm x 0.98mm
Port Location	Bottom


## Evaluation Kit Schematic



## Evaluation Kit BOM

- 3SM222KMB1HA-P, Bottom port digital microphone
- BYPASS CAPACITOR, 0.1uF, 0.1μF ±10% 16V, X5R, 0402
- EVK222KMB1HA-P CIRCUIT PCB

## Evaluation Kit Dimensions



### Disclaimer

1. All information stated herein may change without prior notice, and is provided on an "AS IS" basis for the reference purpose only.  
2. No license of any intellectual property right of 3S is granted by implication, estoppel or otherwise under this document.  
3. 3S makes no warranties, either expressed or implied, including without limitation warranties of non-infringement of intellectual property rights of any third party, regarding the information and specification contained in this document.

## ADDITIONAL INFORMATION

For inquiries, or further information on available products with evaluation kit please visit the 3S website On-line Inquiry at <http://www.3system.com.tw>