SMD TCXO

ASTXR-12-19.200MHz-512242







Moisture Sensitivity Level (MSL) – 1

OVERVIEW:

Abracon's ASTXR series of Temperature Compensated Crystal Oscillators are based on an Advanced-Analog Temperature Compensation Integrated Circuit, incorporated with Rakon's Precision TCXO processing techniques.

This composite enables exceptional frequency stability over temperature ($\leq \pm 0.50$ ppm over -40°C to +85°C). Additionally, high-resolution screening algorithms are employed during the production verification process, ensuring that 100% of these devices are fully compliant to the stringent frequency stability specifications.

For Power Sensitive applications, the ASTXR series provides the ability to preserve consumed power by placing the device in shut-down mode; when not used. This series of devices are ideally suited for GPS and other mobile applications where performance, size, cost and power management are of critical importance.

FEATURES:

- Excellent phase noise performance
- Low power consumption
- Miniature size: 2.5 x 2.0 x 0.8mm SMD
- RoHS compliant
- Temperature stability: ± 0.5 ppm over $-30 \sim +85^{\circ}$ C

- > **APPLICATIONS**:
 - GPS
 - Smartphone
 - PND
 - Communications
 - Consumer electronics
 - Wi-Fi
 - WiMAX/W-LAN

STANDARD SPECIFICATIONS:

Parameters	Minimum	Typical	Maximum	Units	Notes
Nominal Frequency	19.200		MHz		
Supply Voltage (Vdd)	1.71	1.8	1.89	V	
Current Consumption (@Vdd max)			1.5	mA	See Note 2
Operable Temperature Range	-30		+85	° C	
Storage Temperature Range	-40		+85	° C	
Initial Frequency Tolerance @+25°C±2°C at time of shipment			±1	ppm	
Reflow Shift			±1	ppm	After 2 consecutive reflows and 1hr recovery@+25°C
Frequency Stability over Operating Temperature Range			±0.5	ppm	Ref. to $(F_{MAX}+F_{MIN})/2$. See Note 1
Frequency Slope (tested to a minimum of 1 freq. reading every 2°C over -10°C to +60°C)			0.05	ppm/°C	See Note 1
Frequency Drift (calculated from freq. slope with temp. varied at a maximum of 1.92°C/min (0.032°C/s) over -10°C to +60°C)			1.6	ppb/s	See Note 5
Frequency Slope (tested to a minimum of 1 freq. reading every 2°C over -30°C to +85°C)			0.1	ppm/°C	See Note 1
Frequency Drift (calculated from freq. slope with temp. varied at a maximum of 0.96°C/min (0.016°C/s) over -30°C to +85°C)			1.6	ppb/s	See Note 5
Small Thermal Cycle Frequency Slope (measured at 0.5°C intervals over any 5°C heating and 5°C cooling cycle, at a minimum rate of 1°C/min within the operating temperature range)			50	ppb/°C	See Note 6
Small Thermal Cycle Hysteresis (Difference in Frequency measurement over any 5°C heating and cooling cycle, at a minimum rate of 1°C/min within the operating temperature range)			50	ppb (pk-pk)	
Sensitivity vs. Supply Voltage Variations (Vdd±5% @ +25°C)			±0.1	ppm	
Sensitivity vs. Load Variations (±10% load change @ +25°C)			±0.2	ppm	See Note 2

ABRACON IS ISO9001:2008 CERTIFIED



ABRACON CORPORATION Visit www.abracon.com for Terms & Condi 30332 Esperanza, Rancho S tel 949-546-8000 | fax 949

Visit www.abracon.com for Terms & Conditions of Sale **Revised: 07.11.14** 30332 Esperanza, Rancho Santa Margarita, California 92688 tel 949-546-8000 | fax 949-546-8001 | www.abracon.com

SMD TCXO

ASTXR-12-19.200MHz-512242

Parameters	Minimum	Typical	Maximum	Units	Notes
Long Term Stability (frequency drift over 1 year @ +25°C)			±1	ppm	
Output Type	DC Coupled Clipped Sine-wave				See Note 3
Output Voltage Level (@ minimum Vdd)	0.8			V	See Note 2
Output Load Resistance	9	10	11	kΩ	
Output Load Capacitance	9	10	11	pF	
Startup Time (amplitude)			0.5	ms	Within 90% of specified output level
Startup Time (frequency)			2	ms	Within ±0.5ppm of steady state frequency
Phase Noise @ 19.2MHz Carrier (@+25°C)					
@ 1 Hz offset		-64		dBc / Hz	
(a) 10 Hz offset		-94		dBc / Hz	
(a) 100 Hz offset		-117		dBc / Hz	
(a) 1,000 Hz offset		-139		dBc / Hz	
@ 10,000 Hz offset		-150		dBc / Hz	
@ 100,000 Hz offset		-152		dBc / Hz	

Note:

1. Parts should be shielded from drafts causing unexpected thermal gradients. Temperature changes due to ambient air currents on the oscillator can lead to short term frequency drift

- 2. Specified for load stated in the Oscillator Output section at +25°C
- 3. AC-Coupled outputs require an external capacitor, ≥ 1 nF recommended
- 4. Frequency shift ≤ 1 ppm after reliability test conditions (see section 7.0)
- 5. Frequency drift rate is calculated from the equation $ppb/s=°C/s \times ppb/°C$
- 6. Discard the first 0.5°C interval of each heating and cooling cycle

CROSS REFERENCE INFORMATION:

ASTXR-12-19.200MHZ-512242 is equivalent to Rakon P/N 512242.

PART IDENTIFICATIONS:









(Pb) RoHS / RoHS II Compliant



OUTLINE DIMENSION:









Visit www.abracon.com for Terms & Conditions of Sale **Revised: 07.11.14** 30332 Esperanza, Rancho Santa Margarita, California 92688 tel 949-546-8000 | fax 949-546-8001 | www.abracon.com

SMD TCXO

ASTXR-12-19.200MHz-512242



▷ TAPE & REEL:



ATTENTION: Abracon Corporation's products are COTS – Commercial-Off-The-Shelf products; suitable for Commercial, Industrial and, where designated, Automotive Applications. Abracon's products are not specifically designed for Military, Aviation, Aerospace, Life-dependant Medical applications or any application requiring high reliability where component failure could result in loss of life and/or property. For applications requiring high reliability and/or presenting an extreme operating environment, written consent and authorization from Abracon Corporation is required. Please contact Abracon Corporation for more information.

ABRACON IS ISO9001:2008 CERTIFIED



Visit www.abracon.com for Terms & Conditions of Sale **Revised: 07.11.14** 30332 Esperanza, Rancho Santa Margarita, California 92688 tel 949-546-8000 | fax 949-546-8001 | www.abracon.com