

## Adapter Coaxial Connector TNC Jack, Female Socket to TNC Jack, Female Socket 50 Ohms

**RoHS  
Compliant**

Stock No.: 9200650A0138

### FEATURES

- TNC Female to TNC Female
- 50Ω




### Product Description

This TNC Female to TNC Female coaxial adapter provides the ability to connect between TNC Male and TNC Male interface. Interconnection of these interfaces is often found in test lab or in field environments where devices of differing interface types are interconnected.

### General Specifications

Attribute	Value
Adapter Type A	TNC
Adapter Type B	TNC
Gender A	Female
Gender B	Female
Impedance	50Ω
Frequency Range	12 GHz
Body Orientation	Straight
Polarity	Normal
Contact Plating	Gold
Body Plating	Nickel
Contact Material	Brass
Voltage Rating	500 VRMS
Temperature Range	-40°C ~ 155°C

## Product Drawing



## SPECIFICATIONS:

IMPEDANCE: 50 Ohms  
 INTERFACE PER MIL-STD-348, SECTION 313.2  
 FREQUENCY RANGE: 0-12 GHz  
 VSWR:  
 0-5 GHz <1:1.25  
 5-10 GHz <1:1.4  
 10-12 GHz <1:1.55  
 WORKING VOLTAGE: 500 VRMS @ SEA LEVEL

Dimensions: Millimeters (Inches)

## Part Number Table

Part Number	Description
9200650A0138	Adapter Coaxial Connector TNC Jack, Female Socket to TNC Jack, Female Socket 50 Ohms

Important Notice: This data sheet and its contents (the "Information") belong to the members of the EASE group of companies (the "Group") or are licensed to it. No license is granted for the use of it other than for information purposes in connection with the products to which it relates. No license of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate, but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. EASE is the registered trademark of Ease Electronics Co., Limited 2019.