# **ABL8WPS24200**

Regulated Switch Power Supply, 3-phase, 380..500V AC, 24V, 20 A





#### Main

Range of Product	Modicon Power Supply
Product or Component Type	Power supply
Power supply type	Regulated switch mode
Nominal input voltage	380500 V AC three phase L1, L2, L3
Input voltage limits	320550 V AC
Kw Rating	480 W
Output voltage	24 V DC
Power supply output current	20 A
Permissible temporary current boost	1.5 x In for 4 s)
Anti-harmonic filter	Low frequency harmonic currents

#### Complementary

Complementary		
Inrush current	25 A	
Power factor	0.65 at 24 V DC	
Efficiency	92 %	
Output voltage adjustment	2428.8 V adjustable	
Power dissipation in W	38.4 W	
Provided equipment	Power factor correction filter IEC 61000-3-2	
Output protection type	Against overload manual or automatic reset Against overvoltage 3032 V, manual reset Against short-circuits manual or automatic reset Against undervoltage tripping if U < 21.6 V Thermal automatic reset	
Connections - terminals	Removable screw terminal block 2 x 2.5 mm², diagnostic relay Screw type terminals 3 x 0.53 x 4 mm², AWG 22AWG 12) input connection Screw type terminals 1 x 0.51 x 4 mm², AWG 22AWG 12) input ground connection Screw type terminals 4 x 0.54 x 10 mm², AWG 22AWG 8) output connection	
Status LED	Output voltage 1 LED green and red) Output current 1 LED green, red and orange)	
Depth	6.30 in (160 mm)	
Height	5.63 in (143 mm)	
Width	3.78 in (96 mm)	
Net Weight	3.53 lb(US) (1.6 kg)	
Output coupling	Series Parallel	
Marking	CE	
Mounting support	35 x 7.5 mm symmetrical DIN rail 35 x 15 mm symmetrical DIN rail	
Operating position	Vertical	
Supply	SELV EN/IEC 60950-1 SELV EN/IEC 60204-1 SELV IEC 60364-4-41	

#### Environment

ZIIVII OIIII OII	
Standards	CSA C22.2 No 60950-1 UL 508 EN/IEC 62368-1
Product certifications	CCSAus EAC UL RCM
Environmental characteristic	EMC EN 61000-6-1 EMC EN 61000-6-3 EMC EN 55024 EMC EN/IEC 61000-6-4 EMC EN/IEC 61204-3 Safety EN 61204-4 Safety EN/IEC 60950-1
Operating altitude	6561.68 ft (2000 m)
IP degree of protection	IP20 conforming to EN/IEC 60529
Ambient air temperature for operation	122140 °F (5060 °C) with derating factor) -13122 °F (-2550 °C) without)
Ambient Air Temperature for Storage	-40158 °F (-4070 °C)
Relative Humidity	090 % during operation 095 % in storage
Electrical energy source class conforming to IEC 62368-1	ES1
Dielectric strength	3500 V between input and ground 4000 V between input and output 500 V between output and ground

## Ordering and shipping details

0 11 0		
Category	22525 - ABL8 AND ABL7 POWER SUPPLIE	
Discount Schedule	CP12	
GTIN	3389119405645	
Nbr. of units in pkg.	1	
Package weight(Lbs)	4.74 lb(US) (2.151 kg)	
Returnability	Yes	
Country of origin	PH	

## Packing Units

•	
Unit Type of Package 1	PCE
Package 1 Height	5.07 in (12.882 cm)
Package 1 width	6.27 in (15.928 cm)
Package 1 Length	7.26 in (18.442 cm)
Unit Type of Package 2	S06
Number of Units in Package 2	45
Package 2 Weight	242.51 lb(US) (110 kg)
Package 2 Height	28.94 in (73.5 cm)
Package 2 width	23.62 in (60 cm)
Package 2 Length	31.50 in (80 cm)

# Offer Sustainability

Green Premium product		
WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov		
☑ REACh Declaration		
Pro-active compliance (Product out of EU RoHS legal scope) EVEL RoHS  Declaration		
Yes		

RoHS exemption information	<b>™</b> Yes	
China RoHS Regulation	☑ China RoHS Declaration	
Environmental Disclosure	Product Environmental Profile	
Circularity Profile	End Of Life Information	
PVC free	Yes	

#### Contractual warranty


Warranty	18 months

# Product data sheet Dimensions Drawings

# **ABL8WPS24200**

## Regulated Switch Mode Power Supplies

#### Dimensions




ABL 8	a in mm	a in in.	b in mm	b in in.
RPS24030	125	4.92	45	1.77
RPS24050	125	4.92	56	2.20
RPS24100	145	5.71	86	3.39
RPM24200	145	5.71	146	5.75
WPS24200	160	6.30	96	3.78
WPS24400	160	6.30	166	6.54

# **ABL8WPS24200**

#### Regulated Switch Mode Power Supply


#### Internal Wiring Diagram



#### Regulated Switch Mode Power Supply

#### Line Supply Wiring Diagram


Three-phase (L1-L2-L3) 3 x 380 to 500 V



#### Regulated Switch Mode Power Supplies


#### Series or Parallel Connection

#### Series Connection



(1) Two Shottky diodes Imin = power supply In and Vmin = 50 V

#### Parallel Connection



Family	Series	Parallel
ABL 8RPS/8RPM/8WPS	2 products max. (1)	2 products max.

NOTE: Series or parallel connection is only recommended for products with identical references.

For better availability, the power supplies can also be connected in parallel using the ABL8RED24400 Redundancy module.

# **ABL8WPS24200**

# Product data sheet Performance Curves


#### Regulated Switch Mode Power Supplies

#### Derating

The ambient temperature is a determining factor that limits the power an electronic power supply can deliver continuously. If the temperature around the electronic components is too high, their life will be significantly reduced.

The nominal ambient temperature for the Universal range of Phaseo power supplies is 50°C. Above this temperature, derating is necessary up to a maximum temperature of 60°C.

The graph below shows the power (in relation to the nominal power) that the power supply can deliver continuously, depending on the ambient temperature.



X Maximum operating temperature (°C)

ABL 8RPM, ABL 8RPS, ABL 8WPS mounted vertically


Derating should be considered in extreme operating conditions:

- Intensive operation (output current permanently close to the nominal current, combined with a high ambient temperature)
- Output voltage set above 24 Vdc (to compensate for line voltage drops, for example)
- · Parallel connection to increase the total power

#### Regulated Switch Mode Power Supply


#### **Load Limit**

Manual Reset Protection Mode




#### (1) Boost 4s

Automatic Reset Protection Mode



(1) Boost 4s

#### "Boost" Repeat Accuracy



This type of operation is described in detail in the user manual, which can be downloaded from the website.