




AMPSEAL Automotive Plug Connector and Header Assembly (Continued)

Contacts







Туре	Additional Notes	Part Numbers
Socket Contact	Tn	770520-1
Socket Contact	Gold	770520-3
Socket Contact	Tin, Loose Piece	770854-1
Socket Contact	Gold, Loose Piece	770854-3
Wire Seal Plug	"	770678-1

Wire			
Size (AWG)	Ins. Dia. Range	Applicator Part No.**	Hand Too Part No.
20	1.7-2.7 .067106	567333-2	58440-1
18	1.7-2.7 .067106	567333-2	58440-1
16	1.7-2.7 .067106	567333-2	58440-1

[&]quot;'Dash 1 is used in "T" Terminator with automatic equipment. Dash 2 is used in the AMP-O-LECTRIC Model "K" Machine 565435-5.

Refer to Applicator Instruction Sheet Al 8040 for applicator information.

Seal Plug

All circuits are sealed by a diaphragm in the rubber wire seal. During plug connector assembly, the diaphragm is pierced as the contact passes through it. Unused circuit cavities, unless accidentally perforated, will remain sealed. AMPSFAI Automotive Seal Plug 770678-1 is designed to keep out contaminants if diaphragm is pierced.

