# ATOM RS-232 Kit

#### SKU:K046



# Description

**ATOM RS-232** is a TTL-RS232 level-converter designed for use with the M5Atomic module. RS232 is a full-duplex communication protocol standard, which defines the electrical characteristics of the serial communication system. It is a widely used communication protocol in the field of industrial control. MAX232 chip is integrated in the module, which supports bidirectional conversion between TTL level and RS232 level. A DC/DC voltage regulator chip is integrated in the ATOM RS-232, which can directly convert the 12V voltage of the RS232 hub to 5V to supply power for ATOM.

## Product Features

• Compatible ATOM Matrix/ATOM Lite

- Built-in DC/DC
- Full-duplex communication

## Include

• 1x ATOM RS-232

• 1x ATOM Lite

1x Hex Key

• 1x M2\*8mm Hexagon socket cup head machine screw

• 1x 18cm TYPE-C Cable

# Applications

• RS232 Communication

Industrial control node

# Specification

| Specification               | Parameter  |  |
|-----------------------------|------------|--|
| External port               | VH-3.96 4P |  |
| level-conversion IC         | MAX232     |  |
| DC-DC                       | A0Z1282CI  |  |
| Net weight                  | 26g        |  |
| Gross weight                | 36g        |  |
| Product Size                | 24*48*18mm |  |
| Package Size                | 54*54*20mm |  |
| Case Material Plastic( PC ) |            |  |

EasyLoader is a concise and fast program writer, which has a built-in case program related to the product. It can be burned to the main control by simple steps to perform a series of function verification.

Download Windows Version Easyloader

Download MacOS Version Easyloader



**Description:** 

Send and receive the message through RS485, LED is on, press the key to send the message

## Related Link

• Datasheet

• MAX232

• AOZ1282CI

#### Pin Map

| ΑΤΟΜ        | GPIO22 | GPIO19 | <b>5</b> V | GND |
|-------------|--------|--------|------------|-----|
| ATOM RS-232 | RX     | TX     | 5V         | GND |

## Schematic





### Learn



#### **Roller Mill Remote Scale Display**

A practical use of the M5Stack Atom RS232 as part of a remote display.



#### Arduino

• Click here to get Arduino example

#### UIFlow

Clicke here to get UIFlow example

