Specifications are subject to change without notice (18.01.2017)

Proximity Inductive Sensors Standard range, Nickel-Plated Brass Housing Types ICB, M12

Product Description

A family of inductive proximity switches in industrial standard nickel-plated brass housings. They are able to handle applications where

high sensing range is requested. Output is open collector

Output is open collector NPN or PNP transistors.

Туре	
Housing style	
Housing material	
Housing size	
Housing length	
Detection principle	
Sensing distance	
Output type	
Output configuration	
Connection	

· Sensing distance: 2 mm

Short and long body versions

Output: DC 200 mA, NPN or PNP
Normally open, Normally closed
LED indication for output ON

Cable and M12 plug versions
According to IEC 60947-5-2
Higher resistance to magnetic field
CSA certified for Hazardous Locations

Ordering Key

• Rated operational voltage (U_b): 10 - 36 VDC

Protection: reverse polarity, short circuit, transients

• Flush type

•

•

Type Selection

Connec- tion	Body style	Rated operating distance S _n	Ordering no. NPN Normally open	Ordering no. PNP Normally open	Ordering no. NPN Normally closed	Ordering no. PNP Normally closed
Cable	Short	2 mm	ICB 12 SF 02 NO	ICB 12 SF 02 PO	ICB 12 SF 02 NC	ICB 12 SF 02 PC
Plug	Short	2 mm	ICB 12 SF 02 NOM1	ICB 12 SF 02 POM1	ICB 12 SF 02 NCM1	ICB 12 SF 02 PCM1
Cable	Long	2 mm	ICB 12 LF 02 NO	ICB 12 LF 02 PO	ICB 12 LF 02 NC	ICB 12 LF 02 PC
Plug	Long	2 mm	ICB 12 LF 02 NOM1	ICB 12 LF 02 POM1	ICB 12 LF 02 NCM1	ICB 12 LF 02 PCM1

Specifications

Rated operational voltage (U _b)	10 to 36 VDC (ripple incl.)	
Ripple	≤ 10%	
Output current (I _e)	≤ 200 mA @ 50°C (≤ 150 mA @ 50-70°C)	
OFF-state current (I _r)	\leq 50 μ A	
No load supply current (I_0)	≤ 15 mA	
Voltage drop (U _d)	Max. 2.5 VDC @ 200 mA	
Protection	Reverse polarity, short-circuit, transients	
Voltage transient	1 kV/0.5 J	
Power ON delay (t _v)	300 ms	
Operating frequency (f)	≤ 2000 Hz	
Indication for output ON NO version NC version	Activated LED, yellow Target present Target not present	

Indication for short circuit/ overload	LED blinking	
Assured operating sensing distance (S _a)	$0 \leq S_a \leq 0.81 \ x \ S_n$	
Effective operating distance (S _r)	$0.9 \ x \ S_n \le S_r \le 1.1 \ x \ S_n$	
Usable operating distance (S _u)	$0.9 \ x \ S_r \leq S_u \leq 1.1 \ x \ S_r$	
Repeat accuracy (R)	≤ 10%	
Differential travel (H) (Hysteresis)	1 to 20% of sensing dist.	
Ambient temperature Operating Storage	-25° to +70°C (-13° to +158°F) -30° to +80°C (-22° to +176°F)	
Shock and vibration	IEC 60947-5-2/7.4	
Housing material Body Front	Nickel-plated brass Grey thermoplastic polyester	





ICB12SF02NOM1



Specifications (cont.)

Connection Cable	2 m, 3 x 0.25 mm², grey PVC, oil proof M12 x 1	Approvals (cont.) cCSAus Note: The terminal connector	
Plug Degree of protection	IP 67	(versionM1) was not evalu-	
Weight (cable/nuts included) Cable Plug	Max. 120 g Max. 30 g	ated. The suitability of the ter- minal connector should be determined in the end-use application.	
Dimensions	See diagrams below	of the second	
Tightening torque Distance from sensing face from 2 mm to 5 mm > 5 mm	4 Nm 10 Nm	CE-marking	
Approvals UL (cULus), CSA	As Industrial Control Equipment - Proximity Switches. Types 1, 4, 4X or 12. Max ambient temperature 40°C.	EMC protection IEC 61000-4-2 (ESD) IEC 61000-4-3 IEC 61000-4-4 IEC 61000-4-6 IEC 61000-4-8	

Approvals (cont.)		
cCSAus Note: The terminal connector (versionM1) was not evalu- ated. The suitability of the ter- minal connector should be determined in the end-use application.	Equipment for Hazardous Locations. - Class I, Division 2, Groups A, B, C and D. - T5, Enclosure Type 4.	
	CCC is not required for products with a maximum operating voltage of \leq 36 V	
CE-marking	Yes	
EMC protection IEC 61000-4-2 (ESD) IEC 61000-4-3 IEC 61000-4-4 IEC 61000-4-6 IEC 61000-4-8	According to IEC 60947-5-2 8 KV air discharge, 4 KV contact discharge 3 V/m 2 kV 3 V 30 A/m	

Dimensions





Installation

Flush sensor, when installed in damping material, must be according to Picture 1A.



For sensors installed opposite each other, a minimum space of 6 x Sn (the nominal sensing distance) must be observed (See Picture 3).



must be according to Picture 2A.

 Picture 2A

Flush sensors, when installed together in damping material,



Wiring Diagrams





Reduction factors

The rated operating distance is reduced by the use of metals and alloys other than Fe360. The most important reduction factors for inductive proximity sensors are shown in Picture 4.



Delivery Contents

- Inductive proximity switch ICB.
- 2 nuts NPB
- Packaging: plastic bag

Accessories for Plug Versions

	PVC	PUR
3-wire angled connector, 2 m cable	CONB13NF-A2	CONB13NF-A2P
3-wire angled connector, 5 m cable	CONB13NF-A5	CONB13NF-A5P
3-wire angled connector, 10 m cable	CONB13NF-A10	CONB13NF-A10P
3-wire angled connector, 15 m cable	CONB13NF-A15	CONB13NF-A15P
3-wire straight connector, 2m cable		CONB13NF-S2P
3-wire straight connector, 5m cable		CONB13NF-S5P
3-wire straight connector, 10m cable		CONB13NF-S10P
3-wire straight connector, 15m cable		CONB13NF-S15P

For any additional information or different options, please refer to the "General Accessories -Connector Cables -Type CONB1..." datasheets.