



#### Main Features

- ♦ 10.1" WXGA 1280x800 400 nits LED panel
- ◆ 5 points projected capacitive touch with Full IP40 protection
- ♦ 3-Position Enabling switch & E-Stop Button
- ◆ EMC (IEC/EN 61000-6-2/4) compliance
- ◆ System frame ground protection(GPE) design


## Specification

Technical	TP-100-C	Technical	TP-100-C
Data		Data	
Panel	- 10.1", 16:10, WXGA, 1280 x 800	Interface	- Data back-up: 2 x USB 2.0
	- Luminance: 400 cd/m2		- Control connector: HDB-44 female
	- Contrast ratio: 800:1		> Removable HDB-44 control cable (optional)
	- LCD color: 16.7M		> Including power, E-stop buttons, 3-Position
	- Viewing angle: 89 (U), 89 (D), 89 (L),		enabling switch, button switch, USB 2.0 and
	89 (R)		VGA signals
	- Backlight: LED		
Touch	- Touch: 5 points P-Cap	Ratings	- Power supply voltage: 24 Vdc (19.2 to 28.8
	- Touch light transmission: 87%		Vdc)
	- Touch interface: USB		- Current consumption:
	- Anti-scratch surface: 7H hardness		> TP-100-C 0.625A at 24Vdc (max.)

# TP-100-C datasheet



Technical Data	TP-100-C	Technical Data	TP-100-C
Safety	- Emergency stop button (2 NC	Mechanical	- Dimension: 297.3 x 257.2 x 57.2 mm
Elements	channels,		(78.5mm including E-stop button)
	B10d=100,000)		- Weight (without external control cable):
	> Contact function: latching		> TP-100-C 1.5Kg
	> Reset: by rotating		- Front bezel: aluminum magnesium alloy;
	- 3-position enabling switch		color: Black
	(3 channels 2 NO &1 NC,		- Back cover: ABS+PC; color: Pantone 432C
	B10d=100,000)		- IP protection class: Full IP40
Operating	2-position button switch (1NO & 1NC)	Environment	- Operating temperature: 0°C to 50°C
Elements			- Storage temperature: -20°C to 75°C
			- Operating humidity: 5%~90% relative
			humidity, non-condensing
			- Vibration resistance/shock-proof/free-fall
System	- TP-100-C: VGA input	Certifications	- CE (Emission EN61000-6-4; Immunity
	- USB 2.0 upstream		EN61000-6-2 for installation in industrial
			environments)
			- FCC Class A





# Function and Ergonomic design



#### Membrane Keys




The TP-100-C's membrane keys are located at the lower-right of the teach pendant, each membrane key is mapping to the real-keyboard signal, review the key definitions below:


Key Definition	Defined Keyboard Mapping		
M/A	[Ctrl] + [Shift] + [ m ]		
Stop	[Ctrl] + [Shift] + [ s ]		
Play/Pause	[Ctrl] + [Shift] + [p]		
+	[Ctrl] + [Shift] + []]		
-	[Ctrl] + [Shift] + [ [ ]		
Error Log	[Ctrl] + [Shift] + [ e ]		




## Connection example



#### Junction Cable








TP-100 Holders(Option)





# Ordering Information

- TP-100-C (P/N: 10IH0010015X0)

  10.1" multi- touch teach pendant display
- TP-100-VGA-J-Cable (P/N:6030000511X00)
   TP-100-C Junction Cable
- TP-100 Cable (P/N: 686030000003F)

External 3m cable for TP-100-C

(Option)TP-100 Holders (P/N: 98ROBO000011F)

Holder for TP-100-C