

# WL9LGC-3P2452A00

**SMALL PHOTOELECTRIC SENSORS** 



SMALL PHOTOELECTRIC SENSORS



#### Ordering information

Туре	Part no.
WL9LGC-3P2452A00	1080952

Other models and accessories -> www.sick.com/W9

Illustration may differ



#### Detailed technical data

#### Features

Functional principle	Photoelectric retro-reflective sensor
Functional principle detail	Without reflector minimum distance (autocollimation/coaxial optics)
Dimensions (W x H x D)	12.2 mm x 52.2 mm x 23.6 mm
Housing design (light emission)	Rectangular
Mounting hole	M3
Sensing range max.	0 m 3.5 m <sup>1) 2)</sup>
Sensing range	0 m 2.2 m <sup>1) 2)</sup>
Type of light	Visible red light
Light source	Laser <sup>3)</sup>
Light spot size (distance)	Ø 0.4 mm (60 mm)
Wave length	650 nm
Laser class	1 (IEC 60825-1 / CDRH 21 CFR 1040.10 & 1040.11)
Adjustment	IO-Link, Single teach-in button
Pin 2 configuration	External input, Teach-in input, Sender off input, Detection output, logic output, Device contamination alarm output
AutoAdapt	✓
Special applications	Detecting small objects, Detecting transparent objects

 $^{\mbox{1})}$  Reflective tape REF-AC1000.

<sup>2)</sup> To ensure reliable operation, we recommend using REF-AC1000 reflective tape or reflective-tap reflectors such as P41F, PLV14-A, PLH25-M12, or PLH25-D12. Reflectors with large-scale triple structures must only be used if deemed suitable for the application.

 $^{3)}$  Average service life: 50,000 h at  $T_U$  = +25 °C.

SMALL PHOTOELECTRIC SENSORS

#### Mechanics/electronics

Supply voltage U <sub>B</sub>	10 V DC 30 V DC <sup>1)</sup>
Ripple	< 5 V <sub>pp</sub> <sup>2)</sup>
Current consumption	30 mA <sup>3)</sup>
Switching output	PNP <sup>4) 5)</sup>
Output function	Complementary
Switching mode	Light/dark switching <sup>4)</sup>
Output current I <sub>max.</sub>	≤ 100 mA
Response time	≤ 0.5 ms <sup>6)</sup>
Response time Q/ on Pin 2	300 µs 450 µs <sup>6) 7)</sup>
Switching frequency	1,000 Hz <sup>8)</sup>
Switching frequency Q $/$ to pin 2	≤ 1,000 Hz <sup>9)</sup>
Connection type	Male connector M12, 4-pin
Circuit protection	A <sup>10)</sup> B <sup>11)</sup> C <sup>12)</sup>
Protection class	III
Weight	13 g
Polarisation filter	✓
Housing material	Plastic, VISTAL®
Optics material	Plastic, PMMA
Enclosure rating	IP66 IP67 IP69K
Ambient operating temperature	-10 °C +50 °C
Ambient operating temperature extended	-30 °C +55 °C <sup>13) 14)</sup>
Ambient temperature, storage	-30 °C +70 °C
UL File No.	NRKH.E181493
Repeatability Q/ on Pin 2:	150 μs <sup>7)</sup>

 $^{1)}$  Limit values when operated in short-circuit protected network: max. 8 A.

 $^{2)}\,\text{May}$  not fall below or exceed  $\text{U}_{\text{V}}$  tolerances.

- <sup>3)</sup> Without load.
- $^{4)}$  Q = light switching.
- $^{\rm 5)}$  Pin 4: This switching output must not be connected to another output.
- <sup>6)</sup> Signal transit time with resistive load.
- $^{7)}$  Valid for Q  $\backslash$  on Pin2, if configured with software.
- <sup>8)</sup> With light/dark ratio 1:1.
- $^{9)}$  With light / dark ratio 1:1, valid for Q  $\setminus$  on Pin2, if configured with software.

 $^{10)}$  A = V\_S connections reverse-polarity protected.

<sup>11)</sup> B = inputs and output reverse-polarity protected.

 $^{12)}$  C = interference suppression.

 $^{13)}$  As of T\_a = 50 °C, a max. supply voltage V\_max. = 24 V and a max. load current I\_max. = 50 mA is permitted.

 $^{14)}$  Operation below Tu -10 °C is possible if the sensor is already switched on at Tu > -10 °C, then cools down, and the supply voltage is subsequently not switched off. Switching on below Tu -10 °C is not permissible.

SMALL PHOTOELECTRIC SENSORS

#### Safety-related parameters

MTTFD	562 years (EN ISO 13849-1) <sup>1)</sup>
DC <sub>avg</sub>	0 %
T <sub>M</sub> (mission time)	10 years

<sup>1)</sup> Mode of calculation: Parts-Count-calculation.

Communication interface

Communication interface	IO-Link V1.1
Communication Interface detail	COM2 (38,4 kBaud)
Cycle time	2.3 ms
Process data length	16 Bit
Process data structure	Bit 0 = switching signal $Q_{L1}$ Bit 1 = switching signal $Q_{L2}$ Bit 2 15 = empty
VendorID	26
DeviceID HEX	0x800116
DeviceID DEC	838886

Smart Task

Smart Task name	Base logics
Logic function	Direct AND OR WINDOW Hysteresis
Timer function	Deactivated Switch-on delay Off delay ON and OFF delay Impulse (one shot)
Inverter	Yes
Switching frequency	SIO Direct: 1000 Hz <sup>1)</sup> SIO Logic: 1000 Hz <sup>2)</sup> IOL: 900 Hz <sup>3)</sup>
Response time	SIO Direct: 300 $\mu$ s 450 $\mu$ s <sup>1)</sup> SIO Logic: 500 $\mu$ s 600 $\mu$ s <sup>2)</sup> IOL: 500 $\mu$ s 900 $\mu$ s <sup>3)</sup>
Repeatability	SIO Direct: 150 $\mu$ s <sup>1)</sup> SIO Logic: 150 $\mu$ s <sup>2)</sup> IOL: 400 $\mu$ s <sup>3)</sup>
Switching signal	
Switching signal $Q_{L1}$	Switching output
Switching signal $Q_{L2}$	Switching output

<sup>1)</sup> SIO Direct: sensor operation in standard I/O mode without IO-Link communication and without using internal sensor logic or time parameters (set to "direct"/"deactivated").

<sup>2)</sup> SIO Logic: Sensor operation in standard I/O mode without IO-Link communication. Sensor-internal logic or timing parameters plus Automation Functions used.

<sup>3)</sup> IOL: Sensor operation with full IO-Link communication and usage of logic, timing and Automation Function parameters.

SMALL PHOTOELECTRIC SENSORS

#### Diagnosis

0	
Device status	Yes
Quality of teach	Yes
Quality of run	Yes, Contamination display
Classifications	
ECLASS 5.0	27270902
ECLASS 5.1.4	27270902
ECLASS 6.0	27270902
ECLASS 6.2	27270902
ECLASS 7.0	27270902
ECLASS 8.0	27270902
ECLASS 8.1	27270902
ECLASS 9.0	27270902
ECLASS 10.0	27270902
ECLASS 11.0	27270902
ECLASS 12.0	27270902
ETIM 5.0	EC002717
ETIM 6.0	EC002717
ETIM 7.0	EC002717
ETIM 8.0	EC002717
UNSPSC 16.0901	39121528

### Adjustments

Single teach-in button



③ LED indicator yellow: Status of received light beam
④ LED indicator green: power on

- ⑧ Teach-in button

SMALL PHOTOELECTRIC SENSORS

#### **Connection diagram**

Cd-367



#### Characteristic curve



① Reflector PLV14-A / PLH25-M12 / PLH25-D12

② Reflector P41F / reflective tape REF-AC1000

#### Light spot size



#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
60 mm	0.4	0.4
(2.36)	(0.02)	(0.02)
200 mm	3.2	2.4
(7.87)	(0.13)	(0.09)
2,000 mm	40	30
(78,74)	(1.57)	(0.18)
3,500 mm	60	50
(137.80)	(2.36)	(1.97)

① Minimum distance between sensor and reflector

#### Light spot size (detailed view)



① Minimum distance between sensor and reflector

#### Sensing range diagram



② Reflector P41F / reflective tape REF-AC1000

SMALL PHOTOELECTRIC SENSORS

#### Dimensional drawing (Dimensions in mm (inch))

WL9L-3



① Sender and receiver optical axis center

- ② Mounting hole M3 (Ø 3.1 mm)
- ③ LED indicator yellow: Status of received light beam
- ④ LED indicator green: power on

⑤ Connecting cable or connecting cable with connector

(6) Male connector M8, 4-pin

⑦ Male connector M12, 4-pin

#### **Recommended accessories**

Other models and accessories -> www.sick.com/W9

	Brief description	Туре	Part no.
Reflectors			
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm, self-adhesive	REF-AC1000-56	4063030
Others			
N.	<ul> <li>Connection type head A: Female connector, M12, 4-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 4-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals, Uncontaminated zones</li> </ul>	YF2A14- 050VB3XLEAX	2096235
٠.	<ul> <li>Connection type head A: Male connector, M12, 4-pin, straight, A-coded</li> <li>Description: Unshielded</li> <li>Connection systems: Screw-type terminals</li> <li>Permitted cross-section: ≤ 0.75 mm<sup>2</sup></li> </ul>	STE-1204-G	6009932

#### **Recommended services**

Additional services -> www.sick.com/W9

	Туре	Part no.
Function Block Factory		
<ul> <li>Description: The Function Block Factory is an engineering tool for creating device and environment-specific function blocks that enable IO-Link sensors to be integrated into programmable logic controllers. The Function Block Factory supports common programmable logic controllers (PLCs) of various manufacturers such as Siemens, Beckhoff, Rockwell Automation B&amp;R and more. More information on the FBF can be found <a href="https://fbf.cloud.sick.com" target="blank">https://fbf.cloud.sick.com</a></li> <li>Provision: Customers can obtain access to the Function Block Factory and the license via <a href="https://fbf.cloud.sick.com" target="blank">https://fbf.cloud.sick.com</a></li> </ul>	Function Block Factory	On request

# SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# WORLDWIDE PRESENCE:

Contacts and other locations -www.sick.com



Online data sheet

