



SICK Sensor Intelligence.

**COMPACT PHOTOELECTRIC SENSORS** 

COMPACT PHOTOELECTRIC SENSORS



## **Ordering information**

Туре	Part no.
WTB250-2R1641	6044684

Included in delivery: BEF-W250(1)

Other models and accessories → www.sick.com/W250-2

Illustration may differ



## Detailed technical data

#### Features

Functional principle	Photoelectric proximity sensor
Functional principle detail	Background suppression
Dimensions (W x H x D)	20 mm x 60 mm x 43.9 mm
Housing design (light emission)	Rectangular
Sensing range max.	150 mm 500 mm <sup>1)</sup>
Sensing range	150 mm 500 mm <sup>1)</sup>
Focus	Approx. 3°
Type of light	Visible red light
Light source	LED <sup>2)</sup>
Light spot size (distance)	Ø 30 mm (500 mm)
Angle of dispersion	Approx. 3°
Adjustment	Potentiometer, 2 turns <sup>3)</sup> Potentiometer, 2 rotations

 $^{1)}$  Object with 90% remission (based on standard white, DIN 5033).

 $^{2)}$  Average service life: 100,000 h at  $T_U$  = +25 °C.

 $^{\rm (3)}$  With position indicator.

## Mechanics/electronics

Supply voltage U <sub>B</sub>	24 V DC 240 V DC <sup>1)</sup>
	24 V AC/DC 240 V AC/DC <sup>1)</sup>

<sup>1)</sup> +- 10%.

 $^{\mbox{2})}$  Provide suitable spark suppression for inductive or capacitive loads.

<sup>3)</sup> With light/dark ratio 1:1.

 $^{4)}$  Do not bend below 0 °C.

<sup>5)</sup> A = V<sub>S</sub> connections reverse-polarity protected.

<sup>6)</sup> C = interference suppression.

<sup>7)</sup> Reference voltage: 250 V AC.

<sup>8)</sup> The AC/DC devices comply with the Radio Safety Requirements for the industrial sector (Radio Safety Class A). They may cause radio interference if used in a residential area.

COMPACT PHOTOELECTRIC SENSORS

Power consumption	≤ 5 VA
Switching output	Relay, electrically isolated <sup>2)</sup>
Output function	Change-over contacts
Switching mode	Light switching <sup>2)</sup>
Switching current (switching voltage)	3 A (240 V AC) 3 A (30 V DC)
Response time	≤ 15 ms
Switching frequency	33 Hz <sup>3)</sup>
Connection type	Cable, 5-wire, 5 m <sup>4)</sup>
Cable material	Plastic, PVC
Conductor cross section	0.76 mm <sup>2</sup>
Cable diameter	Ø 6.4 mm
Circuit protection	A <sup>5)</sup> C <sup>6)</sup>
Protection class	II <sup>7</sup> )
Overvoltage category	2
Weight	330 g
Housing material	Plastic, ABS
Optics material	Plastic, PMMA
Enclosure rating	IP67
Items supplied	BEF-W250 mounting bracket
Electromagnetic compatibility (EMC)	EN 60947-5-2 <sup>8)</sup>
Ambient operating temperature	-25 °C +55 °C
Ambient temperature, storage	-40 °C +70 °C
UL File No.	NRKH2.E300503 & NRKH8.E300503

<sup>1)</sup> +- 10%.

 $^{\mbox{2})}$  Provide suitable spark suppression for inductive or capacitive loads.

<sup>3)</sup> With light/dark ratio 1:1.

<sup>4)</sup> Do not bend below 0 °C.

 $^{5)}$  A = V\_S connections reverse-polarity protected.

 $^{6)}$  C = interference suppression.

<sup>7)</sup> Reference voltage: 250 V AC.

<sup>8)</sup> The AC/DC devices comply with the Radio Safety Requirements for the industrial sector (Radio Safety Class A). They may cause radio interference if used in a residential area.

# Classifications

ECLASS 5.0	27270904
ECLASS 5.1.4	27270904
ECLASS 6.0	27270904
ECLASS 6.2	27270904
ECLASS 7.0	27270904
ECLASS 8.0	27270904
ECLASS 8.1	27270904
ECLASS 9.0	27270904

COMPACT PHOTOELECTRIC SENSORS

ECLASS 10.0	27270904
ECLASS 11.0	27270904
ECLASS 12.0	27270903
ETIM 5.0	EC002719
ETIM 6.0	EC002719
ETIM 7.0	EC002719
ETIM 8.0	EC002719
UNSPSC 16.0901	39121528

## Dimensional drawing (Dimensions in mm (inch))

WTB250-2, AC/DC, cable



- ① Standard direction of the material being detected
- Axis of sender
- 3 Axis of receiver
- ④ Mounting hole ø 4.2 mm, for M4 hexagon nuts on both sides
- ⑤ Connection cable

COMPACT PHOTOELECTRIC SENSORS

# Adjustments

WTB250-2



- LED indicator green: Stability indicator
   LED indicator yellow: Status of received light beam
- Sensing range adjustment: potentiometer
- Position indicator for sensitivity setting (270°)

# Connection diagram

Cd-163



COMPACT PHOTOELECTRIC SENSORS

### Characteristic curve

WTB250-2, 500 mm





 $\textcircled{\sc 0}$  Sensing range on black, white background

② Sensing range on gray, white background

3 Sensing range on white, white background

## Sensing range diagram

WTB250-2, 500 mm



Sensing range

- ① Sensing range on black, white background
- ② Sensing range on gray, white background
- $\ensuremath{\textcircled{}}$  Sensing range on white, white background

COMPACT PHOTOELECTRIC SENSORS

#### Recommended accessories

Other models and accessories → www.sick.com/W250-2

	Brief description	Туре	Part no.
Others			
	<ul> <li>Connection type head A: Male connector, M12, 5-pin, straight, A-coded</li> <li>Description: Unshielded, Head A: male connector, M12, 5-pin, straight, unshielded, for cable diameter 4 mm 6 mm Head B: -</li> <li>Connection systems: Screw-type terminals</li> <li>Permitted cross-section: ≤ 0.75 mm<sup>2</sup></li> <li>Note: For field bus technology</li> </ul>	STE-1205-G	6022083

# SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# WORLDWIDE PRESENCE:

Contacts and other locations -www.sick.com



Online data sheet

