


863 MHz / 960 MHz / 2450 MHz PCB Antenna (ISM, RFID, IoT, LP-WAN, Smart meters, Wi-Fi 2.4 GHz)



#### General information

This small antenna is intended to be soldered to the main PCB of a mobile device, a router or a gateway. On request, the antenna geometry can be optimized for customer's housing design and material properties.

#### Typical applications

ISM, RFID, IoT (Sigfox, LoRa), LP-WAN, Smart meters, Wi-Fi 2.4 GHz

#### Electrical data

Antenna type	Embedded / internal antenna soldered on the main PCB	
Frequency band	SRD860 (EU), ISM915 (US), ISM2400	
Frequency range [MHz]	863...960	2400...2500
Return loss [dB] <sup>1)</sup>	-8	-8
Peak gain [dBi]	1.6	2.7
Radiation efficiency [%]	73	67
Nominal input impedance [Ohm]	50	
Polarization	linear	
Radiation pattern	omnidirectional	
Maximum input power [W]	5	

#### Mechanical data

Antenna PCB dimensions [mm]	45 x 17.5 x 0.8
PCB material	FR4
Weight [g]	1.1

#### Environmental data

Operating temperature [°C]	-40...+85
Storage temperature [°C]	-40...+85
Ambient relative humidity [%]	0...95
RoHS / REACH compliant	yes / yes

#### Additional information

All electrical data have been obtained in free space on the reference board (not included) with the following dimensions: 120mm x 60mm x 0.8mm. Please note that the performance in the lower frequency bands is dependent on the ground plane length and may degrade in case of reducing the board size.


Other mechanical designs, materials or frequency bands are possible on request.

Further customization, electromagnetic simulations and measurements can be offered on request.


*All information (including technical data and pictures) presented in this document is typical and subject to change without notice. Sevskiy is a registered trade mark of Sevskiy GmbH. Copyright © 2009 - 2023 Sevskiy GmbH. All rights reserved. No warranties.*

863 MHz / 960 MHz / 2450 MHz PCB Antenna (ISM, RFID, IoT, LP-WAN, Smart meters, Wi-Fi 2.4 GHz)

**Measured input impedance matching**





**Coordinate system**



All information (including technical data and pictures) presented in this document is typical and subject to change without notice. Sevskiy is a registered trade mark of Sevskiy GmbH. Copyright © 2009 - 2023 Sevskiy GmbH. All rights reserved. No warranties.

863 MHz / 960 MHz / 2450 MHz PCB Antenna (ISM, RFID, IoT, LP-WAN, Smart meters, Wi-Fi 2.4 GHz)


Radiation pattern (total realized gain, dBi)



All information (including technical data and pictures) presented in this document is typical and subject to change without notice. Sevskiy is a registered trade mark of Sevskiy GmbH. Copyright © 2009 - 2023 Sevskiy GmbH. All rights reserved. No warranties.


863 MHz / 960 MHz / 2450 MHz PCB Antenna (ISM, RFID, IoT, LP-WAN, Smart meters, Wi-Fi 2.4 GHz)

**Product dimensions and recommended layout**



Top layer


Bottom layer



All information (including technical data and pictures) presented in this document is typical and subject to change without notice. Sevskiy is a registered trade mark of Sevskiy GmbH. Copyright © 2009 - 2023 Sevskiy GmbH. All rights reserved. No warranties.

863 MHz / 960 MHz / 2450 MHz PCB Antenna (ISM, RFID, IoT, LP-WAN, Smart meters, Wi-Fi 2.4 GHz)

Antenna placement



All information (including technical data and pictures) presented in this document is typical and subject to change without notice. Sevskiy is a registered trade mark of Sevskiy GmbH. Copyright © 2009 - 2023 Sevskiy GmbH. All rights reserved. No warranties.