

## FM9858B/SF-10 DATA SHEET

# WR-112 Standard Gain Horn Antenna Operating From 7.05 GHz to 10 GHz, 10 dBi Nominal Gain, SMA Female Input Connector, ProLine

The Fairview Microwave FM9858B/SF-10 Proline series standard gain horn antenna (also known as waveguide horn) is part of our huge selection of waveguide antennas. This Fairview Microwave standard gain horn antenna is manufactured with a WR-112 input and a SMA waveguide to coaxial transition adapter. Our standard gain horn antenna, WR-112, has a 10 dBi nominal gain. This WR-112 standard gain horn from Fairview Microwave has a female SMA waveguide to coax transition adapter.

The 10dBi Fairview Microwave WR-112 hornantenna operates from 7.05 GHz to 10 GHz. Fairview Microwave's SMA female WR-112 standard gain horns are available in 10, 15 and 20dBi models with pyramidal shape and rectangular input. It is part of over 40,000 RF, microwave and millimeter wave components available at Fairview Microwave.

Waveguide standard gain horn antennas, such as the FM9858B/SF-10, are used in a wide variety of applications due to their high power handling capability, low loss, high directivity, and near constant electrical performance. The WR-112 FM9858B/SF-10 waveguide horn is US made and TAA compliant. Our WR-112 standard gain horn Proline antennas with SMA female interface can ship same day to anywhere in the world.

## Configuration

Design
Pattern
Polarization
Coaxial Interface

WR-112 Standard Gain Horn

Directional Linear SMA Female

### **Electrical Specifications**

Min	Тур	Max	Units
7.05		10	GHz
	50		Ohms
Gain Horn			
	10		dB
Adapter			
	1.3:1		
		7.05 50 <b>Gain Horn</b> 10 <b>Adapter</b>	7.05 10 50 Gain Horn 10 Adapter

## **Mechanical Specifications**

#### Size

 Length
 3.69 in 93.73 mm

 Width/Diameter
 1.64 in 41.66 mm

 Height
 1.18 in 29.97 mm

 Weight
 1.45 lbs 657.71 g

#### **RF Connector**

Type SMA Female

## **Waveguide Interface**

Waveguide Size WR-112 Flange Type Square Cover



## **Features:**

- WR-112 Rectangular Waveguide Interface
- 7.05 GHz to 10 GHz
- 10 dBi Nominal Gain
- SMA Female Connector

## **Applications:**

- Antenna Measurements
- Wireless Communication
- Laboratory Use
- Microwave Radio Systems

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





## **Environmental Specifications**

**Compliance Certifications** (see product page for current document)

#### **Plotted and Other Data**

2 Dimensional OML Drawing Notes:

FM9858B/SF-10

WR-112 Standard Gain Horn Antenna Operating From 7.05 GHz to 10 GHz, 10 dBi Nominal Gain, SMA Female Input Connector, ProLine from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF ondemand.

For additional information on this product, please click the following link: WR-112 Standard Gain Horn Antenna Operating From 7.05 GHz to 10 GHz, 10 dBi Nominal Gain, SMA Female Input Connector, ProLine FM9858B/SF-10

URL: https://www.fairviewmicrowave.com/standard-gain-horn-0-fm9858b-sf-10-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020

REV 1.1 Page 2 of 3





