

FMWCA1104 DATA SHEET

WR-28 to 2.92mm Female Waveguide to Coax Adapter UBR320 with 26.5 GHz to 40 GHz in Aluminum

The FMWCA1104 is a right angle waveguide to coaxial adapter operating at a frequency range of 26.5 GHz to 40 GHz. This adapter offers a WR-28 waveguide interface size coupled with a precision tolerance UBR320 flange. The FMWCA1104 is constructed of aluminum and painted gray to ensure durability. The coaxial connector offered by this adapter uses an 2.92mm Female connector.

Configuration

Waveguide Size WR-28 Flange UBR320

RF Connector 2.92mm Female Body Geometry Right Angle

Electrical Specifications

Description	Min	Тур	Max	Units
Frequency Range	26.5		40	GHz
VSWR			1.25:1	
Insertion Loss			0.4	dB
Input Power (CW)			20	Watts

Mechanical Specifications

Size

 Length
 1.06 in [26.92 mm]

 Width
 0.75 in [19.05 mm]

 Height
 0.75 in [19.05 mm]

 Weight
 1 lbs [453.59 g]

RF Connector

Connector Type 2.92mm Female

Waveguide Interface

Waveguide Type WR-28
Flange Type UBR320
Body Material and Plating Aluminum

Environmental Specifications

Temperature

Operating Range -20 to +70 deg CStorage Range -40 to +85 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

• Values at +25 °C, sea level unless stated otherwise



Features:

- 26.5 to 40 GHz
 Frequency Range
- WR-28 Waveguide Interface
- UBR320 Flange
- 2.92mm Female RF Interface
- Comprenhensive waveguide offering also include E-Bends, H-Bends, Sections, Filters, Terminations, Couplers, and more.

Applications:

- · Test Benches
- Radar
- Satellite
- · Microwave Radio Systems
- Military and Space
- Communication Systems

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





WR-28 to 2.92mm Female Waveguide to Coax Adapter UBR320 with 26.5 GHz to 40 GHz in Aluminum from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: WR-28 to 2.92mm Female Waveguide to Coax Adapter UBR320 with 26.5 GHz to 40 GHz in Aluminum FMWCA1104

URL: https://www.fairviewmicrowave.com/wr28-2.92mm-female-waveguide-coax-adapter-ubr320-fmwca1104-p.aspx







