

902 to 928 MHz, RFID Flat Panel Antenna, 3 dBi Gain, Type N Male, EVA Radome, RHCP

# LCANFP1066



### **Features**

- · High Performance Multi-tag read/write Capabilities
- Lightweight, Concealable Design
- · Right Hand Circular Polarized

# **Applications**

- · Radio Frequency Identification
- · Inventory Management
- Access Control

- · 902 to 928 MHz Frequency Range
- 2 Meter Cable
- Type N Male Connector
- · Data Collection
- Asset Tracking
- · Livestock Management

### **Description**

L-Com's LCANFP1066 is a RHCP RFID flat panel antenna. The LCANFP1066 with a 3 dBi gain nominal is a Directional antenna. Our 902 to 928 MHz antenna has N Male connector.

With an impedance of 50 Ohms and max input power of 20 Watts, the LCANFP1066 flat panel RHCP antenna is well suited for Radio Frequency Identification tag reading applications. This 902-928 MHz 3 dBi gain RFID antenna is highly directional providing the reader radio the capabilities of simultaneously reading a multitude of RFID tags with a high degree of accuracy.

L-Com's RFID LCANFP1066 has a radome made of EVA in Black color and comes from a facility certified to ISO 9001:2015. This N Male connectized Antenna has an overall length of 11 in, width of 10 in, and weighs 0.4629 lbs. Use our on-line ordering system to purchase your LCANFP1066 RFID Directional RHCP antenna 24 hours a day with same-day shipping and no MOQs (minimum order quantities).

# Configuration

Design Flat Panel **Application Band RFID** Band Type Single Radiation Pattern Directional Polarization **RHCP** RG316 Cable Type Connector Type N Male Lightning Protection DC Grounded

### **Electrical Specifications**

| Description               | Minimum | Typical | Maximum | Units   |
|---------------------------|---------|---------|---------|---------|
| Frequency Range           | 902     |         | 928     | MHz     |
| Input VSWR                |         |         | 1.5:1   |         |
| Impedance                 |         | 50      |         | Ohms    |
| Gain                      |         | 3       |         | dBi     |
| Front to Back Ratio       | 20      |         |         | dB      |
| Horizontal (Azimuth) HPBW |         | 50      |         | Degrees |

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 902 to 928 MHz, RFID Flat Panel Antenna, 3 dBi Gain, Type N Male, EVA Radome, RHCP LCANFP1066



902 to 928 MHz, RFID Flat Panel Antenna, 3 dBi Gain, Type N Male, EVA Radome, RHCP

# The second secon

### LCANFP1066

| Vertical (Elevation) HPBW | 62 |    | Degrees |
|---------------------------|----|----|---------|
| Input Power               |    | 20 | Watts   |
|                           |    |    |         |

# **Mechanical Specifications**

Radome Material EVA

Size

 Length
 11 in [279.4 mm]

 Width
 10 in [254 mm]

 Height
 0.19 in [4.83 mm]

 Weight
 0.4629 lbs [209.97 g]

### Connectors

| Description               | Connector 1   | Connector 2 | Connector 3 |
|---------------------------|---------------|-------------|-------------|
| Body Material and Plating | Brass, Nickel | C           | U           |
|                           |               |             |             |

# **Environmental Specifications**

**Temperature** 

Operating Range -20 to +65 deg C

Compliance Certifications (see product page for current document)

### **Plotted and Other Data**

Notes:

902 to 928 MHz, RFID Flat Panel Antenna, 3 dBi Gain, Type N Male, EVA Radome, RHCP from L-com has same day shipment for domestic and International orders. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

# **L-com CAD Drawing**

