

S S I Z S I Z S I Z

1.85mm Female to 1.85mm Female Right Angle Adapter

RF Adapters Technical Data Sheet

PE1278

Configuration

- 1.85mm Female Connector 1
- 1.85mm Female Connector 2

Features

- Max VSWR of 1.35:1 up to 67 GHz
- 50 µin contact plating

Applications

General Purpose Test

- 50 Ohm
- Right Angle Body Geometry
- Gold Plated Beryllium Copper Contact

Description

Pasternack's PE1278 1.85mm female to 1.85mm female right angle adapter is part of our full line of RF components available for same-day shipping. The 1.85mm connector mates mechanically with commercially available 2.4mm connectors. Our 1.85mm to 1.85mm adapter has a female to female gender configuration built of durable stainless steel. PE1278 1.85mm female to 1.85mm female adapter operates to 67 GHz. The Pasternack RF adapter provides good VSWR of 1.35:1 maximum. This right angle 1.85mm to 1.85mm adapter allows for easier connections in tight spaces.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		67	GHz
VSWR			1.35:1	

Mechanical Specifications

 Size
 0.56 in [14.22 mm]

 Length
 0.312 in [7.92 mm]

 Width
 0.312 in [7.92 mm]

 Height
 0.566 in [14.38 mm]

 Weight
 0.176 lbs [79.83 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 1.85mm Female to 1.85mm Female Right Angle Adapter PE1278

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451





1.85mm Female to 1.85mm Female Right Angle Adapter

RF Adapters Technical Data Sheet

PE1278

Description	Connector 1	Connector 1 Connector 2	
Туре	1.85mm Female	1.85mm Female	
Polarity	Standard	Standard	

Material Specifications

	Connector 1		Connector 2		
Description	n Material	Plating	Material	Plating	
Туре	1.85mm Female		1.85mm Female		
Contact	Beryllium Copper	Gold	Beryllium Copper	Gold	
		50 μin		50 μin	
Insulation	PEI		PEI		
Outer Conductor	Passivated Stainless Steel		Passivated Stainless Steel		
Body	Passivated Stainless Steel		Passivated Stainless Steel		

Compliance Certifications (see product page for current document)

1.85mm Female to 1.85mm Female Right Angle Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 1.85mm Female to 1.85mm Female Right Angle Adapter PE1278

URL: https://www.pasternack.com/1.85mm-female-to-1.85mm-female-right-angle-adapter-pe1278-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

PE1278 CAD Drawing
1.85mm Female to 1.85mm Female Right Angle Adapter

