



# 50 Ohm 2 Way N Power Divider From 8 GHz to 12.4 GHz Rated at 10 Watts

## TECHNICAL DATA SHEET

PE2036

#### 50 Ohm 2 Way N Power Divider From 8 GHz to 12.4 GHz Rated at 10 Watts

#### Configuration

Input Connector	N Female
Frequency Range, GHz	8 to 12.4
Number of Output Ports	2

#### **Electrical Specifications**

Frequency Range, GHz	8 to 12.
Impedance, Ohms	50
Maximum Insertion Loss, dB	1
Maximum Input Power, Watts	10
Maximum Input VSWR	1.6:1
Minimum Isolation, dB	16

### **Mechanical Specifications**

#### Size

Length, in [mm]	2 [50.8]
Width, in [mm]	2.472 [62.79]
Height, in [mm]	1 [25.4]

Compliance Certifications (visit www.Pasternack.com for current document)

#### Plotted and Other Data

Notes: Values at 25 °C, sea level

50 Ohm 2 Way N Power Divider From 8 GHz to 12.4 GHz Rated at 10 Watts from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 50 Ohm 2 Way N Power Divider From 8 GHz to 12.4 GHz Rated at 10 Watts PE2036

URL: http://www.pasternack.com/2-way-n-reactive-power-divider-8-ghz-12.4-ghz-10-watts-pe2036-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

**PE2036 CAD Drawing**50 Ohm 2 Way N Power Divider From 8 GHz to 12.4 GHz Rated at 10 Watts

