

2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25, 0.098 Inches End Launch PCB Connector



RF Connectors Technical Data Sheet

PE45934

Configuration

- 2.4mm Female Connector
- 50 Ohms

Features

- Max. Operating Frequency 50 GHz
- Excellent VSWR of 1.25:1

Gold Plated Beryllium Copper Contact

· Straight Body Geometry

Applications

General Purpose Test

PCB Applications

Description

PE45934 2.4mm female PCB RF connector has a 50 Ohms impedance. Our 2.4mm female PCB connector provides a maximum frequency of 50 GHz. Our high-quality radio frequency coaxial connector is used for general purpose tests and printed circuit board applications. This 2.4mm female RF connector is stocked to be readily available for same business day shipment.

The Pasternack 2.4mm female PCB connector has a maximum VSWR of 1.25:1. The Pasternack 2.4mm PCB connector has a stainless steel body with gold plating. Our PE45934 2.4mm connector uses a gold plated-stainless steel outer conductor. Pasternack's 2.4mm female connector has a maximum operating voltage of 150 Vrms and a dielectric withstanding voltage of 500 Vrms.

Pasternack RF connector has a maximum inner conductor and outer conductor resistance of 4 mOhms and 2.5 mOhms respectively. The radio frequency connector is made from stainless steel material and has a contact life of 500 cycles or more. The Pasternack PE45934 2.4mm connector operates at a temperature range of -40 to +165 deg C. Our female RF connector with PCB termination has a 0.353 dB maximum insertion loss.

This Pasternack 2.4mm female connector will ship the same business day as purchased. Our 2.4mm female connector is part of RF, microwave, and millimeter wave components in stock for local, domestic, and international shipment. For further information on similar products, our expert technical support and trained sales team can get you the ideal RF connector as per your requirements.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		50	GHz
VSWR			1.25:1	
Insertion Loss			0.353	dB
Operating Voltage (AC)			150	Vrms
Impedance		50		Ohms
Dielectric Withstanding Voltage (AC)			500	Vrms
Inner Conductor DC Resistance			4	mOhms
Outer Conductor DC Resistance			2.5	mOhms
Insulation Resistance	5,000			MOhms

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25, 0.098 Inches End Launch PCB Connector PE45934

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25, 0.098 Inches End Launch PCB Connector



RF Connectors Technical Data Sheet

PE45934

RF Leakage	100	dB

Mechanical Specifications

Size

 Length
 0.50 in [12.70 mm]

 Width
 0.30 in [7.62 mm]

 Height
 0.30 in [7.62 mm]

 Weight
 0.00 lbs [0.45 g]

 Mating Cycles
 500 Cycles

Mating Cycles

Mating Torque

500 Cycles

9.74 to 15 in-lbs [1.10 to 1.70 Nm]

Cable Retention Force 4.5 lbs 2.04 kg

Material Specifications

Description	Material	Plating	
Contact	Beryllium Copper	Gold	
Insulation	PEI		
Outer Conductor	Stainless Steel	Gold	
Body	Stainless Steel	Gold	

Environmental Specifications

Temperature

Operating Range -40 to +165 deg C

Humidity MIL-STD-202, Method 106

Thermal Shock MIL-STD-202, Method 107, Condition B Salt Spray MIL-STD-202, Method 101, Condition B

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25, 0.098 Inches End Launch PCB Connector PE45934

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25, 0.098 Inches End Launch PCB Connector



RF Connectors Technical Data Sheet

PE45934

2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25, 0.098 Inches End Launch PCB Connector from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25, 0.098 Inches End Launch PCB Connector PE45934

URL: https://www.pasternack.com/2.4mm-female-pcb-connector-pe45934-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE45934 CAD Drawing

2.4mm Female PCB Mount, Round Contact 50GHz VSWR1.25,

