

Low PIM 4.3-10 Female to 4.3-10 Female Adapter



RF Adapters Technical Data Sheet

PE91464

Configuration

- 4.3-10 Female Connector 1
- 4.3-10 Female Connector 2
- •50 Ohm

- Low PIM Design
- Straight Body Geometry

Features

- Max VSWR of 1.25:1 up to 6 GHz
- PIM levels lower than -160 dBc

Silver Plated Beryllium Copper Contact

Applications

- General Purpose Test
- Low PIM Applications
- Mobile Communications Systems
- Base Stations
- Distributed Antenna Systems (DAS)
- Small Cells
- Feeder Cables

Description

Pasternack's PE91464 4.3-10 female to 4.3-10 female adapter is part of our full line of RF components available for same-day shipping. Our 4.3-10 to 4.3-10 adapter has a female to female gender configuration in a low PIM design. PE91464 4.3-10 female to 4.3-10 female adapter operates to 6 GHz. The Pasternack RF adapter provides excellent VSWR of 1.25:1 maximum and passive intermodulation of -160 dBc maximum.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Minimum	Typical	Maximum	Units
DC		6	GHz
		1.25:1	
		-160	dBc
5,000			MOhms
	DC	DC	DC 6 1.25:1 -160

Electrical Specification Notes: Values at 25° C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 4.3-10 Female to 4.3-10 Female Adapter PE91464

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



Low PIM 4.3-10 Female to 4.3-10 Female Adapter



RF Adapters Technical Data Sheet

PE91464

Mechanical Specifications Size

Description	Connector 1	Connector 2
Туре	4.3-10 Female	4.3-10 Female
Polarity	Standard	Standard
Mating Cycles	500	500

Material Specifications

Material	Plating	Material	Ploting
		mercorial	Plating
I.3-10 Female		4.3-10 Female	
eryllium Copper	Silver	Beryllium Copper	Silver
PTFE		PTFE	
Bronze	Tri-Metal	Bronze	Tri-Metal
Brass	Tri-Metal	Brass	Tri-Metal
	eryllium Copper PTFE Bronze	eryllium Copper Silver PTFE Bronze Tri-Metal	eryllium Copper Silver Beryllium Copper PTFE PTFE Bronze Tri-Metal Bronze

Environmental Specifications

Temperature

Operating Range

-55 to +120 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 4.3-10 Female to 4.3-10 Female Adapter PE91464

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451



Low PIM 4.3-10 Female to 4.3-10 Female Adapter

RF Adapters Technical Data Sheet

PE91464

Low PIM 4.3-10 Female to 4.3-10 Female Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 4.3-10 Female to 4.3-10 Female Adapter PE91464

URL: https://www.pasternack.com/4.3-10-female-4.3-10-female-straight-adapter-pe91464-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

PE91464 CAD Drawing

Low PIM 4.3-10 Female to 4.3-10 Female Adapter

