

## Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter



## RF Adapters Technical Data Sheet

PE91473

#### Configuration

- 7/16 DIN Female Connector 1
- QD 4.3-10 Female Connector 2
- 50 Ohm

#### **Features**

- Max VSWR of 1.2:1 up to 6 GHz
- PIM levels lower than -163 dBc

#### **Applications**

- Allows Connection Between Series
- General Purpose Test
- Low PIM Applications
- Mobile Communications Systems

Low PIM Design

Straight Body Geometry

- Silver Plated Beryllium Copper Contact
- Quick Disconnect (QD) on the 4.3-10 Interface
- Base Stations
- Distributed Antenna Systems (DAS)
- Small Cells

Feeder Cables

#### **Description**

Pasternack's PE91473 7/16 DIN female to 4.3-10 female QD adapter is part of our full line of RF components available for same-day shipping. Our 7/16 DIN to 4.3-10 adapter has a female to female gender configuration in a low PIM design. PE91473 7/16 DIN female to 4.3-10 female adapter operates to 6 GHz. The Pasternack RF adapter provides excellent VSWR of 1.2:1 maximum and passive intermodulation of -163 dBc maximum.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/ disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

#### **Electrical Specifications**

| Description             | Minimum | Typical | Maximum | Units |
|-------------------------|---------|---------|---------|-------|
| Frequency Range         | DC      |         | 6       | GHz   |
| VSWR                    |         |         | 1.2:1   |       |
| Passive Intermodulation |         |         | -163    | dBc   |
|                         |         |         |         |       |

**Electrical Specification Notes:** Values at 25° C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter PE91473

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



## Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter



## RF Adapters Technical Data Sheet

PE91473

# Mechanical Specifications Size

| Description   | Connector 1     | Connector 2   |  |
|---------------|-----------------|---------------|--|
| Туре          | 7/16 DIN Female | 4.3-10 Female |  |
| Polarity      | Standard        | Standard      |  |
| Mating Cycles | 500             | 500           |  |
|               |                 |               |  |

#### **Material Specifications**

| Description     | Connector 1      |           | Connector 2      |           |  |
|-----------------|------------------|-----------|------------------|-----------|--|
|                 | Material         | Plating   | Material         | Plating   |  |
| Туре            | 7/16 DIN Female  |           | QD 4.3-10 Female |           |  |
| Contact         | Beryllium Copper | Silver    | Beryllium Copper | Silver    |  |
| Insulation      | PTFE             |           | PTFE             |           |  |
| Outer Conductor | Bronze           | Tri-Metal | Bronze           | Tri-Metal |  |
| Body            | Brass            | Tri-Metal | Brass            | Tri-Metal |  |

### **Environmental Specifications**

**Temperature** 

Operating Range

-40 to +155 deg C

Compliance Certifications (see product page for current document)

**Plotted and Other Data** 

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter PE91473

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451



## Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter



## RF Adapters Technical Data Sheet

PE91473

Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter PE91473

URL: https://www.pasternack.com/7-16-din-female-4.3-10-female-straight-adapter-pe91473-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

**PE91473 CAD Drawing**Low PIM 7/16 DIN Female to 4.3-10 Female QD Adapter

