

Low PIM 4.3-10 Female to N Male Adapter



RF Adapters Technical Data Sheet

PE91479

Configuration

- 4.3-10 Female Connector 1
- N Male Connector 2
- •50 Ohm

Low PIM Design

Straight Body Geometry

Features

- Max VSWR of 1.25:1 up to 6 GHz
- PIM levels lower than -160 dBc

Silver Plated Beryllium Copper Contact

Applications

- Allows Connection Between Series
- General Purpose Test
- Low PIM Applications
- Mobile Communications Systems
- Base Stations
- Distributed Antenna Systems (DAS)
- Small Cells

Feeder Cables

Description

Pasternack's PE91479 4.3-10 female to type N male adapter is part of our full line of RF components available for same-day shipping. Our 4.3-10 to type N adapter has a female to male gender configuration in a low PIM design. PE91479 4.3-10 female to type N male adapter operates to 6 GHz. The Pasternack RF adapter provides excellent VSWR of 1.25:1 maximum and passive intermodulation of -160 dBc maximum.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		6	GHz
VSWR			1.25:1	
Passive Intermodulation			-160	dBc

Electrical Specification Notes: Values at 25° C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 4.3-10 Female to N Male Adapter PE91479

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



Low PIM 4.3-10 Female to N Male Adapter



RF Adapters Technical Data Sheet

PE91479

Mechanical Specifications Size

Description	Connector 1	Connector 2
Туре	4.3-10 Female	N Male
Polarity	Standard	Standard
Mating Cycles	500	500

Material Specifications

	Connector 1		Connector 2		
Description	Material	Plating	Material	Plating	
Туре	4.3-10 Female		N Male		
Contact	Beryllium Copper	Silver	Beryllium Copper	Silver	
Insulation	PTFE		PTFE		
Outer Conductor	Bronze	Tri-Metal			
Body	Brass	Tri-Metal	Brass	Tri-Metal	
Gasket			Silicone Rubber		
Coupling Nut			Brass	Tri-Metal	

Environmental Specifications

Temperature

Operating Range -40 to +155 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 4.3-10 Female to N Male Adapter PE91479

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451



Low PIM 4.3-10 Female to N Male Adapter



RF Adapters Technical Data Sheet

PE91479

Low PIM 4.3-10 Female to N Male Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM 4.3-10 Female to N Male Adapter PE91479

URL: https://www.pasternack.com/4.3-10-female-n-male-straight-adapter-pe91479-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

PE91479 CAD DrawingLow PIM 4.3-10 Female to N Male Adapter

