

## HN Tee Adapter Male-Female-Male



# RF Adapters Technical Data Sheet

PE9578

## Configuration

- HN Male Connector 1
- HN Female Connector 2

- 50 Ohms
- Tee Body Geometry

## **Features**

- HN interface compliant with MIL-STD-348
- Contact plating according to QQ-S-365

Silver Plated Contact

## **Applications**

• General Purpose Test

## Description

Pasternack's PE9578 HN tee adapter male-female-male is part of our full line of RF components available for same-day shipping. Our HN tee adapter has a male-female-male gender configuration. Tee adapters (also called tee connectors) are three port devices that can be used to split or combine a signal. Unlike power dividers/combiners, however, they do not provide matched impedance at all ports.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

### **Mechanical Specifications**

^	:_	
•	17	$\sim$

 Length
 2.55 in [64.77 mm]

 Width
 0.88 in [22.35 mm]

 Height
 1.49 in [37.85 mm]

 Weight
 0.281 lbs [127.46 g]

Description	Connector 1	Connector 2
Туре	HN Male	HN Female
Polarity	Standard	Standard
Interface Specification	MIL-STD-348	MIL-STD-348

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: HN Tee Adapter Male-Female-Male PE9578

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451



# HN Tee Adapter Male-Female-Male

## RF Adapters Technical Data Sheet

PE9578

### **Material Specifications**

	Connector 1		Connector 2	
Description	Material	Plating	Material	Plating
Туре	HN Male		HN Female	
Contact		Silver		Silver
		QQ-S-365		QQ-S-365
Insulation	PTFE		PTFE	
Outer Conductor			Brass	Nickel
				QQ-N-290
Body	Brass	Nickel		
		QQ-N-290		
Gasket	Silicone Rubber		Silicone Rubber	
Coupling Nut	Brass	Nickel		
		QQ-N-290		

### **Environmental Specifications**

Temperature

Operating Range -65 to +165 deg C

Compliance Certifications (see product page for current document)

### **Plotted and Other Data**

Notes:

HN Tee Adapter Male-Female-Male from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: HN Tee Adapter Male-Female-Male PE9578

URL: https://www.pasternack.com/hn-male-female-male-tee-adapter-pe9578-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

# PE9578 CAD Drawing

HN Tee Adapter Male-Female-Male

